MUSIC SYNTHESIZER

SY77

SERVICE MANUAL

■ **CONTENTS** (目次)

LM 006983 *Second Edition*

YAMAHA CORP.
HAMAMATSU. JAPAN
2.27K·885 ⓔ Printed in Japan '90.01

IMPORTANT NOTICE

This manual has been provided for the use of authorized Yamaha Retailers and their service personnel. It has been assumed that basic service procedures inherent to the industry, and more specifically Yamaha Products, are already known and understood by the users, and have therefore not been restated.

WARNING: Failure to follow appropriate service and safety procedures when servicing this product may result in personal injury, destruction of expensive components and failure of the product to perform as specified. For these reasons, we advise all Yamaha product owners that all service required should be performed by an authorized Yamaha Retailer or the appointed service representative.

IMPORTANT: The presentation or sale of this manual to any individual or firm does not constitute authorization, certification, recognition of any applicable technical capabilities, or establish a principle-agent relationship of any form.

The data provided is believed to be accurate and applicable to the unit(s) indicated on the cover. The research, engineering, and service departments of Yamaha are continually striving to improve Yamaha products. Modifications are, therefore, inevitable and changes in specification are subject to change without notice or obligation to retrofit. Should any discrepancy appear to exist, please contact the distributor's Service Division.

WARNING: Static discharges can destroy expensive components. Discharge any static electricity your body may have accumulated by grounding yourself to the ground buss in the unit (heavy gauge black wires connect to this buss).

IMPORTANT: Turn the unit OFF during disassembly and parts replacement. Recheck all work before you apply power to the unit.

This product uses a lithium battery for memory back-up.

WARNING: Lithium batteries are dangerous because they can be exploded by improper handling. Observe the following precautions when handling or replacing lithium batteries.

- Leave lithium battery replacement to qualified service personnel.
- Always replace with batteries of the same type.
- When installing on the PC board, solder using the connection terminals provided on the battery cells. Never solder directly to the cells. Perform the soldering as quickly as possible.
- Never reverse the battery polarities when installing.
- Do not short the batteries.
- Do not attempt to recharge these batteries.
- Do not disassemble the batteries.
- Never heat batteries or throw them into fire.

ADVARSEL!

Lithiumbatteri. Eksplosionsfare.

Udskiftning må kun foretages af en sagkyndig, og som beskrevet i servicemanualen.

SPECIFICATIONS

- **Tone generator:** Realtime Convolution and Modulation (RCM)
  AWM2: 16 bit linear waveform data, maximum 48k Hz sampling frequency
  AFM: 6 operators, 45 algorithms, 3 feedback loops, 16 waveforms, modulation from AWM output
  Filter: Time variant IIR (infinite impulse response) digital filters, 2 filters for each element (maximum of 8 filters per voice)
  Maximum simultaneous notes: 16 notes AWM + 16 notes AFM
  Maximum simultaneous timbres: 16
  Note assignment: Last note priority, DVA (dynamic voice allocation)
- **Keyboard:** 61 notes, key velocity sensitivity, channel aftertouch
- **DSP effects:** (reverb effect + modulation effect) × 2
  Reverb effects: 40 types
  Modulation effects: 4 types
- **Sequencer:** Tracks: 16 (15 tracks + 1 pattern track)
  Songs: 1
  Resolution: 1/96 of a quarter note (for internal clock)
  Maximum simultaneous notes: 32
  Capacity: approximately 16,000 notes
  Patterns: 99
  Recording: realtime/step/punch in
- **Memory:** Preset memory: 128 voices, 16 multis
  Internal memory: 64 voices, 16 multis
  Waveform memory: 2 Mwords (4 Mbytes), 112 sounds
  Card slots: synthesizer data × 1, waveform data × 1
  Disk: 3.5" floppy disk drive
  (713K byte formatted)
- **Controllers:** Wheels: PITCH, MODULATION 1, MODULATION 2
  Slider: OUTPUT 1, OUTPUT 2, DATA ENTRY
  Knobs: LCD contrast, click volume
  Dial: data entry dial
  Panel switches: MODE × 5, EDIT/COMPARE, COPY/SAVE, EF.BYPASS, SEQUENCER × 7, SHIFT, function × 8, EXIT, PAGE ◁ ▷, JUMP/MARK, cursor △ ▽ ◁ ▷, −1/NO, +1/YES, numeric keypad 0−9, MEMORY × 4, BANK × 4, voice select × 16
- **Display:** LCD: 240 × 64 pixels (backlit)
  LED: red × 11, red/green × 21
- **Terminals:** Audio output: OUTPUT 1 (L/MIX, L/MONO, R/MIX R), OUTPUT 2 (L, R), PHONES Controller: BREATH, FOOT VOLUME, FOOT CONTROLLER, SUSTAIN, FOOT SWITCH
  MIDI: IN, OUT, THRU
- **Power requirements:** U.S. & Canadian models: 120V
  European & Australian models: 220−240V
- **Power consumption:** U.S. & Canadian models: 28W
  European & Australian models: 28W
- **Dimensions:** 1046 (W) × 407 (D) × 119 (H) mm
- **Weight:** 17kg
- **Output level:** Headphones: −1dBm
  Output terminals: −10dBm
- **Accessory:** Floppy disk (3.5 inch) × 1
  Plug cover × 1

■総合仕様

●音　源
　音源形式　：RCM音源
　(Realtime Convolution and Modulation)
　AWM2：16ビットリニア波形，サンプリング周波数最大48kHz
　1音(エレメント)につき1オクターブ 12 dBのデジタルフィルターを2個搭載
　AFM：6オペレータ，45アルゴリズム，3系統フィードバック，16波形
　AWM2の出力波形による変調が可能
　1音(エレメント)につき1オクターブ 12 dBのデジタルフィルターを2個搭載
　フィルター　：時変形デジタルフィルター×最大8/ボイス
　：各フィルターはLPF,HPFの切り替えができ，この組合せによりBPFやロールオフ24dBのLPFとしても使用可能
　：レゾナンス可変で発振領域までカバー
　最大同時発音数　：AWM2：16音 ＋ AFM：16音
　最大同時音色数　：16
　発音形式　：後着優先，DVA
●鍵　盤　：61キー/イニシャル&チャンネルアフタータッチ付き
●エフェクタータイプ　：(リバーブ系＋モジュレーション系)×2系統
　リバーブ系　：40タイプ
　モジュレーション系：4タイプ
●シーケンサー
　トラック数　：16トラック(含むパターントラック1)
　ソング　：1
　分解能　：♩/96(内部クロック時)
　最大同時発音数　：32
　最大記憶音数　：約16000音
　パターン数　：99
　録音方式　：リアルタイム/ステップ/パンチイン
●プリセットメモリー　：ボイス：128＋マルチ：16
●インターナルメモリー：ボイス：64＋マルチ：16
●波形用メモリー　：2Mワード(4Mバイト)
　：楽器音×92
　：リズム×20
●カードスロット　：音色パラメータ用×1
　MCD64：1バンク
　※ 1バンク：64ボイス＋16マルチ＋ 1システム
　：波形用× 1(512Kワード)
●3.5インチFDD　：1(フォーマット時713KB)
●Wheel　：ピッチベンド，モジュレーション1，モジュレーション2
●スライダーボリューム：アウトプットボリューム1・2，データエントリー
●ロータリーボリューム：LCDコントロール，クリックボリューム
●ダイヤル　：データエントリー

●パネルスイッチ　Mode：5 Voice, Multi, Song, Pattern, Utility
　Edit：2 Edit/Compare, Copy
　Effect bypass：1
　Memory select：4 Preset 1, Preset 2, Internal, Card
　Bank select：4 A～D
　Voice select：16 1～16
　Page：3 Page＋, Page－, Jump/Mark
　テンキー：12 0～9, Enter, －
　Data Entry：2 Inc, Dec
　カーソル：4 ←, →, ↑, ↓
　Function：10 Function 1～8, Shift, Exit
　Sequencer：7 Run, Stop, Rec, Top, Rew, FF, Auto, Locate
●LCD　：240×64Dots(バックライト付き)
●LED　：Red×11
　：Red/Green×21
●音声出力　：4 Output 1(L/Mix L/Mono, R/Mix R), Output 2(L,R)
●ヘッドフォン　：1
●コントローラー　：6 Foot control, Foot volume, Foot switch, Sustain switch, Breath control
●MIDI　：3 IN, OUT, THRU
●ヘッドフォン出力レベル　：－1dBm
●リア出力端子レベル　：－10dBm
●電源電圧　：100V
●消費電力　：20W
●寸　法　：1046(W)×407(D)×119(H)mm
●重　量　：17kg
●付属品　：デモディスク1枚
　(3.5インチフロッピーディスク)
　：プラグカバー 1個

SY77

■PANEL LAYOUT（パネルレイアウト）

●Front Panel（フロントパネル）



●Rear Panel（リアパネル）



SY77

■CIRCUIT BOARD LAYOUT（ユニットレイアウト）



● Wiring（配線図）



SY77

■BLOCK DIAGRAM（ブロックダイアグラム）



■ DISASSEMBLY PROCEDURE（分解手順）

1. Bottom Cover Assembly (refer to fig. 1.)

1-1. Remove the nineteen (19) screws Ⓐ (4.0×10 bonding head tapping screw), the Bottom cover assembly can be removed.
This will give you access to the DM1, DM2, PS circuit boards, Floppy disk drive unit and Wheel assembly.

1．底板Ass'yの外し方（図1参照）

1-1. Ⓐのネジ19本(4×10ボンディングBタイトネジ)を外して取り外します。



(fig. 1)

2. DM1 Circuit Board (refer to fig.2)

2-1. Remove the Bottom cover assembly. (see procedure 1.)

2-2. Remove the six (6) screws Ⓑ (4.0×10 bind head tapping screw), the DM1 circuit board can be raised.
After the connectors have been disconnected, the DM1 circuit board can be taken out of the unit completely.

2．DM1シートの外し方（図2参照）

2-1. 底板Ass'yを外します。(1項参照)

2-2. Ⓑのネジ6本(4×10バインドタッピングネジ)と束線を外して取り外します。

3. DM2 Circuit Board (refer to fig.2)

3-1. Remove the Bottom cover assembly. (see procedure 1.)

3-2. Remove the six (6) screws Ⓒ (4.0×10 bind head tapping screw), the DM2 circuit board can be raised.
After the connectors have been disconnected, the DM2 circuit board can be taken out of the unit completely.

3．DM2シートの外し方（図2参照）

3-1. 底板Ass'yを外します。(1項参照)

3-2. Ⓒのネジ6本(4×10バインドタッピングネジ)と、束線を外して取り外します。

4. PS Circuit Board (refer to fig. 2.)

4-1. Remove the Bottom cover assembly. (see procedure 1.)

4-2. Remove the screw Ⓓ (4.0×10 bonding head tapping screw) to remove the AC panel.

4-3. The PS circuit board can be removed by removing the four (4) screws Ⓔ (4.0×10 bind head tapping screw) and disconnecting the connectors.

4．PSシートの外し方（図2参照）

4-1. 底板Ass'yを外します。(1項参照)

4-2. Ⓓのネジ1本(4×10ボンディングBタイトネジ)を外し、ACパネルを外しておきます。

4-3. Ⓔのネジ4本(4×10バインドタッピングネジ)と、束線を外して取り外します。

5. Power Transformer (refer to fig. 2.)

5-1. Remove the Bottom cover assembly. (see procedure 1.)

5-2. Remove the PS circuit board. (see procedure 4.)

5-3. Remove the two (2) screws Ⓕ (4.0 × 10 bind head tapping screw) to remove the Power transformer.

6. Floppy Disk Drive Unit (refer to fig.2 and fig. 3)

6-1. Remove the Bottom cover assembly. (see procedure 1.)

6-2. Remove the three (3) screws Ⓖ (4.0 × 10 bind head tapping screw) and disconnect the connectors, the Floppy disk drive unit can be taken out of the SY77 unit.

6-3. To remove the FDD holder from the Floppy disk drive unit, remove the four (4) screws Ⓗ (3.0 × 6 bind head tapping screw).

5. 電源トランスの外し方（図2参照）

5-1. 底板Ass'yを外します。(1項参照)

5-2. PSシートを外します。(4項参照)

5-3. Ⓕのネジ2本(4 ×10バインドタッピングネジ) を外します。

6. FDDの外し方（図2, 3参照）

6-1. 底板Ass'yを外します。(1項参照)

6-2. Ⓖのネジ3本(4 ×10バインドタッピングネジ) と束線を外して、FDD Ass'yを取り外します。FDD金具はⒽのネジ4本(3 × 6バインド小ネジ) を外して取り外します。



(fig. 2)



(fig. 3)

7. CARD Circuit Board (refer to fig. 4)

7-1. Remove the Bottom cover assembly. (see procedure 1.)

7-2. Remove the DM1 circuit board. (see procedure 2.)

7-3. After the three (3) screws Ⓘ (4.0 × 10 bind head tapping screw) have been removed, the CARD circuit board can be removed.

8. JKAN Circuit Board (refer to fig. 4 and fig. 5)

8-1. Remove the Bottom cover assembly. (see procedure 1.)

8-2. Remove the DM1 and DM2 circuit boards. (see procedures 2 and 3.)

8-3. Remove the ten (10) screws Ⓚ (4.0 × 10 bonding head tapping screw) on the rear panel and three (3) screws Ⓙ (4.0 × 10 bind head tapping screw), the JKAN circuit board can be removed.

7. CARDシートの外し方（図4参照）

7-1. 底板Ass'yを外します。(1項参照)

7-2. DM1シートを外します。(2項参照)

7-3. Ⓘのネジ3本(4 ×10バインドタッピングネジ) と、束線を外して取り外します。

8. JKANシートの外し方（図4, 5参照）

8-1. 底板Ass'yを外します。(1項参照)

8-2. DM1シートとDM2シートを外します。
(2と3項参照)

8-3. Ⓙのネジ3本(4 ×10バインドタッピングネジ) と、リアパネル側より止めているⓀのネジ10本(4 ×10ボンディングBタイトネジ)と、束線を外して取り外します。



(fig. 4)

• Rear View



(fig. 5)

9. Keyboard Assembly (refer to fig. 6.)

9-1. Remove the Bottom cover assembly. (see procedure 1.)

9-2. Remove the DM1 and DM2 circuit boards. (see procedures 2 and 3.)

9-3. Remove the PS circuit board. (see procedure 4.)

9-4. The Keyboard assembly can be removed by removing the five (5) screws Ⓛ (4.0×10 bind head tapping screw) and four (4) screws Ⓜ (4.0×16 bind head tapping screw).

9. 鍵盤Ass'yの外し方（図6参照）

9-1. 底板Ass'yを外します。(1項参照)

9-2. DM1シートとDM2シートを外します。
(2と3項参照)

9-3. PSシートを外します。(4項参照)

9-4. Ⓛのネジ5本(4×10バインドタッピングネジ)とⓂのネジ4本(4×16バインドタッピングネジ)を外して取り外します。



(fig. 6)

10. PNAB and PNC Circuit Boards (refer to fig. 4 and fig.7)

10-1. Pull out the konbs on the Control panel.

10-2. Remove the Bottom cover assembly. (see procedure 1.)

10-3. Remove the DM1 and DM2 circuit boards. (see procedures 2 and 3.)

10-4. Remove the PS circuit board. (see procedure 4.)

10-5. Remove the JKAN circuit board. (see procedure 8.)

10-6. Remove the Keyboard assembly. (see procedure 9.)

10-7. Remove the fourteen (14) screws Ⓝ (4.0×10 bind head tapping screw) to remove the Center angle bracket.

10. PNABシートとPNCシートの外し方（図4，7参照）

10-1. パネル表側より、スライドボリューム類のツマミを抜きとっておきます。

10-2. 底板Ass'yを外します。(1項参照)

10-3. DM1シートとDM2シートを外します。
(2と3項参照)

10-4. PSシートを外します。(4項参照)

10-5. JKANシートを外します。(8項参照)

10-6. 鍵盤Ass'yを外します。(9項参照)

10-7. Ⓝのネジ14本(4×10バインドタッピングネジ)を外して、センターアングルを取り外します。

10-8. PNAB circuit board removal
10-8-1. Remove the CARD circuit board. (see procedure 6.)
10-8-2. Remove the three (3) screws Ⓞ (4.0×10 bind head tapping screw) to remove the Card guide.
10-8-3. After the seven (7) screws Ⓟ (4.0×10 bind head tapping screw) have been removed, the PNAB circuit board can be removed.
* The PNAB circuit board is connected to the PNC circuit board with wire harnesses.
10-9. PNC circuit board removal
10-9-1. After the eight (8) screws Ⓠ (4.0×10 bind head tapping screw) have been removed, the PNC circuit board can be removed.

10-8. PNABシートの外し方
10-8-1. CARDシートを外します。(6項参照)
10-8-2. Ⓞのネジ3本(4×10バインドタッピングネジ)を外してカードガイドを取り外します。
10-8-3. Ⓟのネジ7本(4×10バインドタッピングネジ)を外せばPNABシートが外れます。
※束線も一緒に外す場合は、PNCシートも外して行って下さい。
10-9. PNCシートの外し方
10-9-1. Ⓠのネジ8本(4×10バインドタッピングネジ)を外して取り外します。
※束線も一緒に外す場合は、PNABシートも外して行って下さい。



(fig. 7)

11. LCD Circuit Board (refer to fig. 8)
11-1. Remove the Bottom cover assembly. (see procedure 1.)
11-2. Remove the DM1 and DM2 circuit boards. (see procedures 2 and 3.)
11-3. Remove the PS circuit board. (see procedure 4.)
11-4. Remove the JKAN circuit board. (see procedure 8.)
11-5. Remove the Keyboard assembly. (see procedure 9.)
11-6. Remove the PNAB circuit board. (see procedure 10.)
11-7. The LCD circuit board can be removed by removing the four (4) screws Ⓡ (3.0×B bind head tapping screw).

11. LCDシートの外し方 (図8参照)
11-1. 底板Ass'yを外します。(1項参照)
11-2. DM1とDM2シートを外します。(2と3項参照)
11-3. PSシートを外します。(4項参照)
11-4. JKANシートを外します。(8項参照)
11-5. 鍵盤Ass'yを外します。(9項参照)
11-6. PNABシートを外します。(10項参照)
11-7. Ⓡのネジ4本(3×8バインドタッピングネジ)を外せばLCDシートが外れます。



(fig. 8)

12. Wheel Assembly (refer to fig. 9)

12-1. Remove the Bottom cover assembly. (see procedure 1.)

12-2. After the six (6) screws Ⓢ (3.0×8 bonding head tapping screw) have been removed, the Wheel assembly can be removed.

12. ホイールAss'yの外し方（図9参照）

12-1. 底板を外します。

12-2. Ⓢのネジ6本(3×8ボンディングBタイトネジ)と束線を外して取り外します。



(fig. 9)

13. Rotary Encoder Knob (Data Entry)

13-1. Remove the Bottom cover assembly. (see procedure 1.)

13-2. Remove the DM1 and DM2 circuit boards. (see procedures 2 and 3.)

13-3. Remove the PS circuit board. (see procedure 4.)

13-4. Remove the JKAN circuit board. (see procedure 8.)

13-5. Remove the Keyboard assembly. (see procedure 9.)

13-6. Remove the PNC circuit board. (see procedure 10.)

13-7. Pull out the Rotary encoder knob on the PNC circuit board.

13. ロータリーエンコーダツマミ(データエントリー)の外し方

13-1. 底板Ass'yを外します。(1項参照)

13-2. DM1とDM2シートを外します。(2と3項参照)

13-3. PSシートを外します。(4項参照)

13-4. JKANシートを外します。(8項参照)

13-5. 鍵盤Ass'yを外します。(9項参照)

13-6. PNCシートを外します。(10項参照)

13-7. PNCシートから、ロータリーエンコーダツマミを外します。

3. PNAB Circuit Board Wire Harness
Route this wire harness as far as possible away from harness A (power supply line for the EL panel), then attach tape as shown in the figure below.

3．PNABシート束線
この束線は出来るだけ束線Aより離し、そして下図のようにテープを貼って下さい。



(Fig. 3)

■LSI PIN DESCRIPTION (LSI端子機能表)

• **HD6475328CP-10 <H8/532>** (XG944B00) CPU (Central Processing Unit)

PIN NO.	NAME	I/O	FUNCTION	PIN NO.	NAME	I/O	FUNCTION
1	XTAL	I	Clock	43	P50/A8	O	Address bus
2	Vss	I	Ground	44	P51/A9	O	
3	P10/φ	O	System clock	45	P52/A10	O	
4	P11/E	O	Enable	46	P53/A11	O	
5	P12/$\overline{BACK}$	O	Bus acknowledge	47	P54/A12	O	
6	P13/$\overline{BREQ}$	I	Bus request	48	P55/A13	O	
7	P14/$\overline{WAIT}$	I	Wait	49	P56/A14	O	
8	P15/$\overline{IRQ0}$	I	Interrupt request 0	50	P57/A15	O	
9	P16/$\overline{IRQ1}$	I	Interrupt request 1	51	P60/A16	O	
10	P17/TMO	O	8-bit timer output	52	P61/A17	O	
11	P20/$\overline{AS}$	O	Address strobe	53	P62/A18	O	
12	P21/R/$\overline{W}$	O	Read/Write	54	P63/A19	O	
13	P22/$\overline{DS}$	O	Data strobe	55	Vcc		Power supply
14	P23/$\overline{RD}$	O	Read control	56	P70/TMCI	I	8-bit timer clock input
15	P24/$\overline{WR}$	O	Write control	57	P71/FTI1	I	Free running timer input capture (8-bit timer counter reset input)
16	Vcc		Power supply	58	P72/FTI2	I	
17	MD0	I	Mode control	59	P73/FTI3/TMRI	I	
18	MD1	I		60	P74/FTOB1/FTCI1	O/I	Free running timer output compare B/ Free running timer counter clock
19	MD2	I		61	P75/FTOB2/FTCI2	O/I	
20	$\overline{STBY}$	I	Standby	62	P76/FTOB3/FTCI3	O/I	
21	$\overline{RES}$	I	Reset	63	P77/FTOA1	O	Free running timer output compare A1
22	NMI	I	Non-maskable interrupt	64	Vss		Ground
23	NC			65	AVss		Analog ground
24	Vss		Ground	66	P80/AN0	I	Port 8
25	P30/D0	I/O	Data bus	67	P81/AN1	I	
26	P31/D1	I/O		68	P82/AN2	I	
27	P32/D2	I/O		69	P83/AN3	I	
28	P33/D3	I/O		70	P84/AN4	I	
29	P34/D4	I/O		71	P85/AN5	I	
30	P35/D5	I/O		72	P86/AN6	I	
31	P36/D6	I/O		73	P87/AN7	I	
32	P37/D7	I/O		74	AVcc		Analog power supply
33	P40/A0	O	Address bus	75	P90/FTOA2	O	Free running timer output compare A2
34	P41/A1	O		76	P91/FTOA3	O	Free running timer output compare A3
35	P42/A2	O		77	P92/PW1	O	Pulse width
36	P43/A3	O		78	P93/PW2	O	
37	P44/A4	O		79	P94/PW3	O	
38	P45/A5	O		80	P95/TXD	O	Transmit data
39	P46/A6	O		81	P96/RXD	I	Receive data
40	P47/A7	O		82	P97/SCK	I/O	Serial clock
41	Vss		Ground	83	Vss		Ground
42	Vss			84	EXTAL	I	Clock

• **HD63C01Y0F64** (XF148A00) CPU (SEQ.)

PIN NO.	NAME	I/O	FUNCTION	PIN NO.	NAME	I/O	FUNCTION
1	Vss	I	Ground	33	Vcc		DC Supply (+5V)
2	XTAL	I	Clock (8MHz)	34	A15	O	Address bus
3	EXTAL	I		35	A14	O	
4	MP0	I	Mode program	36	A13	O	
5	MP1	I		37	A12	O	
6	$\overline{RES}$	I	Reset	38	P11	O	
7	$\overline{STBY}$	I	Stand-by mode signal	39	P10	O	
8	NMI	I	Non-maskable interrupt	40	A9	O	
9	P20/TIN	I/O	Port 2	41	A8	O	
10	P21/TOUT1	I/O		42	Vss		Ground
11	P22/SCLK	I/O		43	A7	O	Address bus
12	P23/RX	I/O		44	A6	O	
13	P24/TX	I/O		45	A5	O	
14	P25/TOUT2	I/O		46	A4	O	
15	P26/TOUT3	I/O		47	A3	O	
16	P27/TCLK	I/O		48	A2	O	
17	P50/$\overline{IRQ1}$	I/O	Port 5	49	A1	O	
18	P51/$\overline{IRQ2}$	I/O		50	A0	O	
19	P52/$\overline{MR}$	I/O		51	D7	I/O	Data bus
20	P53/HALT	I/O		52	D6	I/O	
21	P54/$\overline{IS}$	I/O		53	D5	I/O	
22	P55/$\overline{OS}$	I/O		54	D4	I/O	
23	P56	I/O		55	D3	I/O	
24	P57	I/O		56	D2	I/O	
25	P60	I/O	Port 6	57	D1	I/O	
26	P61	I/O		58	D0	I/O	
27	P62	I/O		59	$\overline{BA}$	O	Bus available
28	P63	I/O		60	$\overline{LIR}$	O	Load instruction resistor
29	P64	I/O		61	R/$\overline{W}$	O	Read/Write control
30	P65	I/O		62	$\overline{WR}$	O	Write
31	P66	I/O		63	$\overline{RD}$	O	Read
32	P67	I/O		64	E	O	Enable

• **YM3413** (XE449A00) LDSP (Digital Signal Proccesor)

PIN NO.	NAME	I/O	FUNCTION	PIN NO.	NAME	I/O	FUNCTION
1	VDD		DC supply (+5V)	21	A5	O	Address bus
2	D7	I/O	Data bus	22	A6	O	
3	D6	I/O		23	A7	O	
4	D5	I/O		24	A8	O	
5	D4	I/O		25	A9	O	
6	D3	I/O		26	A10	O	
7	D2	I/O		27	A11	O	
8	D1	I/O		28	A12	O	
9	D0	I/O		29	A13	O	
10	SI0	I	Serial data input	30	A14	O	
11	SI1	I		31	A15	O	
12	SYW	I	Sync pulse	32	A16	O	
13	$\overline{WE}$	O	Write enable	33	SO0	O	Sarial data output
14	$\overline{OE}$	O	Output enable	34	XCLK	I	Clock
15	A0	O	Address bus	35	$\overline{IC}$	I	Initial Clear
16	A1	O		36	$\overline{CRS}$	I	CD counter reset
17	A2	O		37	CDI	I	CD input
18	A3	O		38	CDo	O	CD output
19	A4	O		39	SO1	O	Serial data output
20	Vss		Ground	40	CLK	I	Clock

• **YM3415** (XE450A00) LEF (Effect Processor)

PIN NO.	NAME	I/O	FUNCTION	PIN NO.	NAME	I/O	FUNCTION
1	VDD		Power supply	21	A7	O	Address bus
2	SI0	I	Serial data input	22	A6	O	
3	SI1/TST1	I		23	A5	O	
4	SO0	O	Serial data input	24	A4	O	
5	SO1	O		25	A3	O	
6	XCLK	I	Clock	26	A2	O	
7	CDO	O	CD data output	27	A1	O	
8	CDI	I	CD data input	28	A0	O	
9	$\overline{CRS}$/$\overline{CE}$	I	CD counter reset	29	$\overline{RAS}$	O	DRAM control
10	$\overline{WR}$	I	Write control	30	$\overline{CAS}$	O	DRAM control
11	A/$\overline{D}$	I	Address/data parameter select	31	$\overline{WE}$	O	WE signal
12	PD0	I/O	Data bus	32	$\overline{OE}$	O	OE signal
13	PD1	I/O		33	D3	I/O	Data bus
14	PD2	I/O		34	D2	I/O	
15	PD3	I/O		35	D1	I/O	
16	PD4	I/O		36	D0	I/O	
17	PD5	I/O		37	$\overline{TST2}$	I	Internal test
18	PD6	I/O		38	SYW	I	Sync pulse
19	PD7	I/O		39	CLK	I	Clock
20	Vss		Ground	40	$\overline{IC}$	I	Initial clear

• **YM3029** (XF237A00) AFDO (Floating Point Converter)

PIN NO.	NAME	I/O	FUNCTION	PIN NO.	NAME	I/O	FUNCTION
1	DVDD		Digital power supply (+5V)	15	SHA	I	Sample and hold input (Channel A)
2	LE	O	Latch enable	16	EXG		Exponent ground
3	DAB	O	Channel A/B data output	17	EXG		
4	SYW	I	Sync pulse	18	EXI	I	Exponent input
5	CLK	I	Clock	19	EXO	O	Exponent output
6	ϕ1	O	Clock for DAC	20	AVSS		Analog power supply (−5V)
7	DGND		Digital ground	21	AVDD		Analog power supply (+5V)
8	ADVV		Analog power supply (+5V)	22	SI1	I	Serial data input 1 (Channel A)
9	AVSS		Analog power supply (−5V)	23	VLA0	I	Volume level select (Channel A)
10	SHB	I	Sample and hold input (Channel B)	24	VLA1	I	
11	CH4	O	Output (Channel 4)	25	SI2	I	Serial data input 2 (Channel B)
12	CH3	O	Output (Channel 3)	26	VLB0	I	Volume level select (Channel B)
13	CH2	O	Output (Channel 2)	27	VLB1	I	
14	CH1	O	Output (Channel 1)	28	4/2	I	Channel number select (4 or 2-channel)

• **YM7102** (XG996A00) PAN (Panning Processor)

PIN NO.	NAME	I/O	FUNCTION	PIN NO.	NAME	I/O	FUNCTION
1	A0	I	Address bus	41	LB/ACC8	O	L channel data
2	D7	I/O	Data bus	42	L9/ACC9	O	
3	D6	I/O		43	L10/ACC10	O	
4	D5	I/D		44	L11/ACC11	O	
5	D4	I/D		45	L12/ACC12	O	
6	D3	I/D		46	L13/ACC13	O	
7	D2	I/O		47	L14/ACC14	O	
8	D1	I/O		48	L15/ACC15	O	
9	D0	I/O		49	R0/ACC16	O	R channel data
10	IN1	I	Data from OPS	50	R1/ACC17	O	
11	IN0	I		51	R2/ACC18	O	
12	SI2	I	Data from PAN (cathcade input)	52	R3/ACC19	O	
13	SI1	I		53	R4	O	
14	$\overline{\text{TEGS3}}$	I	Test pin	54	R5	O	
15	$\overline{\text{TEGS2}}$	I		55	R6	O	
16	$\overline{\text{TEGS1}}$	I		56	R7	O	
17	$\overline{\text{TEGS0}}$	I		57	R8	O	
18	NC			58	R9	O	
19	CDO	O	Control data for DSP	59	R10	O	
20	CRS	O	Sync pulse for CD	60	R11	O	
21	S1	O	Signal to DSP	61	R12	O	
22	S2	O		62	R13	O	
23	SYW	O	Sync pulse for DSP	63	R14	O	
24	DSPCLK	O	Clock for DSP	64	R15	O	
25	MODE	I	Output mode (L:16bits DAC H:20bits DAC)	65	NC		
26	$\overline{\text{IC}}$	I	Initial clear	66	$\overline{\text{TTIM}}$	I	Test pin
27	$\overline{\text{SYNC}}$	I	Sync pulse	67	$\overline{\text{TEG1}}$	I	
28	ϕM	I	Clock	68	$\overline{\text{TEG0}}$	I	
29	Vss		Ground	69	$\overline{\text{TRD}}$	I	Chip select
30	Vss			70	$\overline{\text{CS2}}$	I	
31	VDD		Power supply	71	$\overline{\text{CS1}}$	I	
32	VDD			72	VDD		Power supply
33	L0/ACC0	O	L channel data	73	CS0	I	Chip select
34	L1/ACC1	O		74	A7	I	Address bus
35	L2/ACC2	O		75	A6	I	
36	L3/ACC3	O		76	A5	I	
37	L4/ACC4	O		77	A4	I	
38	L5/ACC5	O		78	A3	I	
39	L6/ACC6	O		79	A2	I	
40	L7/ACC7	O		80	A1	I	

• **μPD71055C** (XB361001) PPI (Programmable Peripheral Interface)

PIN NO.	NAME	I/O	FUNCTION	PIN ND.	NAME	I/D	FUNCTION
1	PO3	I/O	Port 0	21	P13	I/O	Port 2
2	PO2	I/O		22	P14	I/O	
3	PO1	I/O		23	P15	I/O	
4	PO0	I/O		24	P16	I/O	
5	$\overline{\text{RD}}$	I	Read control	25	P17	I/O	
6	$\overline{\text{CS}}$	I	Chip Select	26	VDD		DC Supply
7	GND		DC Supply (0V)	27	D7	I/O	Data bus
8	A1	I	Port address	28	D6	I/O	
9	A2	I		29	D5	I/D	
10	P27	I/O	Port 2	30	D4	I/D	
11	P26	I/O		31	D3	I/O	
12	P25	I/O		32	D2	I/O	
13	P24	I/O		33	D1	I/O	
14	P20	I/O		34	D0	I/O	
15	P21	I/O		35	$\overline{\text{RESET}}$	I	Reset
16	P22	I/O		36	$\overline{\text{WR}}$	I	Write control
17	P23	I/O		37	P07	I/O	Port 0
18	P10	I/O	Port B	38	P06	I/O	
19	P11	I/O		39	P05	I/O	
20	P12	I/O		40	P04	I/O	

• **YM7103** (XG993A00) EGM2 (Envelope Generator)

PIN NO.	NAME	I/O	FUNCTION	PIN NO.	NAME	I/O	FUNCTION
1	A0	I	Address bus	41	NC		
2	D7	I/O	Data bus	42	KON	O	Key on data
3	D6	I/O		43	E0	O	Envelope data, Pitch data (portament), Pitch envelope data
4	D5	I/O		44	E1	O	
5	D4	I/O		45	E2	O	
6	D3	I/O		46	E3	O	
7	D2	I/O		47	E4	O	
8	D1	I/O		48	E5	O	
9	D0	I/O		49	E6	O	
10	NC			50	E7	O	
11	TST10	O	Test pin	51	E8	O	
12	TST9	O		52	E9	O	
13	TST8	O		53	E10	O	
14	TST7	O		54	E11	O	
15	TST6	O		55	E12	O	
16	TST5	O		56	E13	O	
17	TST4	O		57	NC		
18	TST3	O		58	NC		
19	TST2	O		59	NC		
20	TST1	O		60	NC		
21	TST0	O		61	NC		
22	ϕM0	O	Clock	62	NC		
23	XTAL	O	Quartz crystal	63	NC		
24	EXTAL	I		64	NC		
25	$\overline{IC}$	I	Initial clear	65	NC		
26	$\overline{SYO}$	O	Sync pulse	66	NC		
27	$\overline{SYI}$	I	Sync pulse	67	NC		
28	ϕMI	I	Clock	68	NC		
29	Vss		Ground	69	NC		
30	Vss			70	NC		
31	NC			71	$\overline{TRD}$	I	Test pin
32	VDD		Power supply	72	$\overline{VDD}$		Power supply
33	NC			73	$\overline{CS0}$	I	Chip select
34	NC			74	CS1	I	
35	NC			75	CS2	I	
36	$\overline{TEGS2}$	I	Test pin	76	A5	I	Address bus
37	$\overline{TEGS1}$	I		77	A4	I	
38	$\overline{TEGS0}$	I		78	A3	I	
39	$\overline{TS01}$	O	Test pin	79	A2	I	
40	$\overline{TS00}$	O		80	A1	I	

• **WD37C65B-JM00** (XH129A00) FDC (Floppy Disk Controller)

PIN NO.	NAME	I/O	FUNCTION	PIN NO.	NAME	I/O	FUNCTION
1	$\overline{RD}$	I	Read control	23	XT2	I	XTAL osc. in
2	$\overline{WR}$	I	Write control	24	$\overline{DRV}$	I	Drive type
3	$\overline{CS}$	I	Chip select	25	$\overline{XT1}$	O	XTAL osc. drive
4	A0	I	Register select	26	XT1	I	XTAL osc. in
5	$\overline{DACK}$	I	DMA acknowledge	27	PCVAL	I	Precompensation value
6	TC	I	Terminal Count	28	$\overline{HS}$	O	Head select (Side select)
7	DB0	I/O	Data bus	29	$\overline{WE}$	O	Write enable
8	DB1	I/O		30	$\overline{WD}$	O	Write data
9	DB2	I/O		31	$\overline{DIRC}$	O	Direction control
10	DB3	I/O		32	$\overline{STEP}$	O	Step pulse
11	DB4	I/O		33	$\overline{DS1}$	O	Drive select 1
12	DB5	I/O		34	Vss		Ground
13	DB6	I/O		35	$\overline{DS2}$	O	Drive select 2
14	DB7	I/O		36	$\overline{MO1/DS3}$	O	Motor ON 1/Drive select 3
15	DMA	O	Direct memory access request	37	$\overline{MO2/DS4}$	O	Motor ON 2/Drive select 4
16	$\overline{IRO}$	O	Interrup request	38	$\overline{HDL}$	O	Head loaded
17	$\overline{DCHGEN}$	I	Disk change enable	39	$\overline{RPM/RWC}$	O	Revolutions per minute/Reduced write current
18	$\overline{LDOR}$	I	Load operations register	40	$\overline{DCHG}$	I	Disk change
19	$\overline{LDCR}$	I	Load control register	41	$\overline{WP}$	I	Write protected
20	$\overline{RST}$	I	Reset	42	$\overline{TR00}$	I	Track 00 signal
21	$\overline{RDD}$	I	Read disk data	43	$\overline{IDX}$	I	Index
22	$\overline{XT2}$	O	XTAL osc. drive	44	Vcc		Power supply

• YM7107 (XG994A00) OPS3 (Operator)

PIN NO.	NAME	I/O	FUNCTION	PIN NO.	NAME	I/O	FUNCTION
1	A0	I	Address bus	41	DA8	O	D/A signal (straight binary)
2	D7	I/O	Data bus	42	DA9	O	
3	D6	I/O		43	DA10	O	
4	D5	I/O		44	DA11	O	
5	D4	I/O		45	DA12	O	
6	D3	I/O		46	DA13	O	
7	D2	I/O		47	DA14	O	
8	D1	I/O		48	DA15	O	(MSB)
9	D0	I/O		49	SH1	O	Sample and hold
10	E13	I	Envelope data, Pitch envelope data, Pitch data	50	SH2	O	
11	E12	I		51	SC0	O	Channel distribution
12	E11	I		52	SC1	O	
13	E10	I		53	SC2	O	
14	E9	I		54	SO0	O	Serial data (2 compl. 16bits LSB first)
15	E8	I		55	SO1	O	
16	E7	I		56	NC		
17	E6	I		57	NC		
18	E5	I		58	NC		
19	E4	I		59	NC		
20	E3	I		60	NC		
21	E2	I		61	NC		
22	E1	I		62	NC		
23	E0	I		63	NC		
24	KON	I	Phase reset for phase acumulator	64	NC		
25	$\overline{IC}$	I	Initial clear	65	NC		
26	NC			66	NC		
27	$\overline{SYNC}$	I	Sync pulse (127C127)	67	NC		
28	ϕM	I	Clock	68	Vss		
29	Vss		Ground	69	SI0	I	Serial data
30	Vss			70	SI1	I	
31	VDD		Power supply	71	NC		
32	VDD			72	VDD		Power supply
33	DA0	O	(LSB)	73	$\overline{CS0}$	I	Chip select
34	DA1	O	D/A signal (straight binary)	74	CS1	I	
35	DA2	O		75	CS2	I	
36	DA3	O		76	A4	I	Address bus
37	DA4	O		77	A3	I	
38	DA5	O		78	A2	I	
39	DA6	O		79	A1	I	
40	DA7	O		80	Vss		Ground

• HD637B01Y (XG950A00) CPU (PKS)

PIN NO.	NAME	I/O	FUNCTION	PIN NO.	NAME	I/O	FUNCTION
1	Vss		Ground	33	Vcc		DC Supply (+5V)
2	XTAL	I	Clock (8MHz)	34	P47	O	Port 4
3	EXTAL	I		35	P46	O	
4	MP0	I	Mode program	36	P45	O	
5	MP1	I		37	P44	O	
6	$\overline{RES}$	I	Reset	38	P43	O	
7	$\overline{STBY}$	I	Stand-by mode signal	39	P42	O	
8	NMI	I	Non-maskable interrupt	40	P41	O	
9	P20	I/O	Port 2	41	P40	O	
10	P21	I/O		42	Vss		Ground
11	P22	I/O		43	P17	O	Port 1
12	P23	I/O		44	P16	O	
13	P24	I/O		45	P15	O	
14	P25	I/O		46	P14	O	
15	P26	I/O		47	P13	O	
16	P27	I/O		48	P12	O	
17	P50	I/O	Port 5	49	P11	O	
18	P51	I/O		50	P10	O	
19	P52	I/O		51	P37	I/O	Port 3
20	P53	I/O		52	P36	I/O	
21	P54	I/O		53	P35	I/O	
22	P55	I/O		54	P34	I/O	
23	P56	I/O		55	P33	I/O	
24	P57	I/O		56	P32	I/O	
25	P60	I/O	Port 6	57	P31	I/O	
26	P61	I/O		58	P30	I/O	
27	P62	I/O		59	P74	O	Port 7
28	P63	I/O		60	P73	O	
29	P64	I/O		61	P72	O	
30	P65	I/O		62	P71	O	
31	P66	I/O		63	P70	O	
32	P67	I/O		64	E	O	Enable

• YM7119 (XG995A00) M3 (AWM Tone generator & Digital Filter)

PIN NO.	NAME	I/O	FUNCTION	PIN NO.	NAME	I/O	FUNCTION
1	INDV0	O	Individual output 0 (8 channels)	65	WA8	O	Wave memory address bus
2	INDV1	O	Individual output 1 (8 channels)	66	WA9	O	
3	OPZ	I	MELIN input select (Ⓗ OPZ, Ⓛ PAN)	67	WA10	O	
4	DIOUT0	O	Stereo output (L & R)	68	WA11	O	
5	DIOUT1	O	Assignable output (ch.0 & ch.4)	69	WA12	O	
6	DIOUT2	O	Assignable output (ch.1 & ch.5)	70	WA13	O	
7	DIOUT3	O	Assignable output (ch.2 & ch.6)	71	WA14	O	
8	DIOUT4	O	Assignable output (ch.3 & ch.7)	72	NC		
9	MELIN	I	MEL formatted signal input	73	WA15	O	
10	LSB/MSB	I	Individual output mode select	74	WA16	O	
11	TTPAD0	I/O	(Ⓗ MSB first, Ⓛ LSB first)	75	WA17	O	
12	TTPAD1	I/O		76	WA18	O	
13	NC			77	WA19	O	
14	TTPAD2	I/O		78	WA20	O	
15	TTPAD3	I/O		79	WA21	O	
16	TTPAD4	I/O		80	WA22	O	
17	TTPAD5	I/O		81	WA23	O	
18	NC			82	A0	I	CPU address bus
19	TTPAD6	I/O	Test pin	83	A1	I	
20	TTPAD7	I/O		84	A2	I	
21	NC			85	A3	I	
22	TTPAD8	I/O		86	A4	I	
23	TTPAD9	I/O		87	A5	I	
24	NC			88	D0	I/O	CPU data bus
25	TTPAD10	I/O		89	NC		
26	TTPAD11	I/O		90	D1	I/O	
27	DIIN0	I	Individual input 0 (8 channels)	91	D2	I/O	
28	DIIN1	I	Individual input 1 (8 channels)	92	D3	I/O	
29	WD0	I/O		93	D4	I/O	
30	WD1	I/O		94	D5	I/O	
31	WD2	I/O		95	D6	I/O	
32	WD3	I/O		96	D7	I/O	
33	NC			97	S/HSC0	I	Sample and hold set timing 0~3
34	WD4	I/O		98	S/HSC1	I	
35	WD5	I/O		99	S/HSC2	I	
36	WD6	I/O		100	S/HSC3	I	
37	WD7	I/O		101	S/HEN	O	Sample and hold enable
38	WD8	I/O	Wave memory data	102	S/H0	O	Sample and hold 0~3
39	WD9	I/O		103	S/H1	O	
40	NC			104	S/H2	O	
41	NC			105	S/HRCA	I	Sample and hold reset A and B
42	WD10	I/O		106	S/HRCB	I	
43	WD11	I/O		107	$\overline{IC}$	I	Initial clear
44	NC			108	Vss		Ground
45	WD12	I/O		109	XTAL	O	Clock
46	WD13	I/O		110	EXTAL	I	
47	WD14	I/O		111	NC		
48	Vss		Ground	112	FCLKOUT	O	Sync. signal on 2 chips mode
49	VDD		Power supply	113	FCLKIN	I	
50	WD15	I/O		114	NC		
51	$\overline{MSBW}$	D	Wave data MSB write signal	115	CLK3	O	6.144MHz clock
52	$\overline{LSBW}$	O	Wave data LSB write signal	116	VDD		Power supply
53	$\overline{OE}$	O	Output enable for wave data	117	SYWIN	I	Sync. signal for MEL format
54	ODD/EVEN	I	Odd/Even select on 2 chips mode	118	CLKMEL	O	3.072MHz clock for MEL format
55	SINGLE/DUAL	I	Wave memory single/dual mode	119	NC		
56	WA0	O	select (Ⓗ: dual·2 chips mode,	120	DACLE	O	Latch enable for PCM56 (DAC)
57	WA1	O	Ⓛ: single·1 chip mode)	121	SYWOUT	O	Sync pulse for MEL format
58	WA2	O		122	SYW64	O	6.144MHz sync. signal
59	WA3	O		123	$\overline{IRQ}$	O	Interrupt request (open drain)
60	WA4	O	Wave memory address bus	124	$\overline{CS}$	I	Chip select
61	WA5	O		125	R/W	I	Read/Write control
62	WA6	O		126	CHPIN	I	EG lowest ch. detect
63	WA7	O		127	CHPOUT	O	EG lowest ch. detect
64	NC			128	KSYNC	I	Key on sync. signal from AFM

■IC BLOCK DIAGRAM (ICブロック図)

- **74F00PC** (IG063690)
  Quad 2 Input NAND



- **SN74HC02N** (IR000250)
  Quad 2 Input NOR



- **SN74LS04N** (IG027020)
- **SN74HCU04N** (IG142250)
- **SN74HC04NSR** (XD830A00)
- **HD74LS05P** (IG052600)
  Hex Inverter



- **SN74ALS08N** (XA876001)
  Quad 2 Input AND



- **SN74HC14N** (IR001450)
  Hex Inverter



- **74F32PC** (IG058990)
- **SN74HC32N** (IR003250)
- **SN74ALS32N** (XA055001)
- **SN74LS32N** (IG049850)
  Quad 2 Input OR



- **SN74HC74N** (IR007450)
- **SN74ALS74N** (XA196A00)
  Dual D-Type Flip-Flop



INPUTS				OUTPUTS	
PR	CLR	CLK	D	Q	Q̄
L	H	X	X	H	L
H	L	X	X	L	H
L	L	X	X	H	H
H	H	↑	H	H	L
H	H	↑	L	L	H
H	H	L	X	Q_0	$\bar{Q}_0$

- **74F138PC** (IG120090)
- **SN74ALS138N** (IG149600)
- **SN74HC138N** (IR013850)
  3 to 8 Demultiplexer



- **SN74HC139N** (IR013950)
  Dual 2 to 4 Demultiplexer



- **SN74ALS245AN** (IG149900)
- **TC74HC245P** (IR024500)
- **SN74LS245** (IG044600)

Octal 3-State Bus Transceiver



- **SN74HC273N** (IR027350)

Octal D-Type Flip-Flop



- **SN74HC367N** (IR036750)

Hex 3-State Bus Buffer



- **HD74LS670P** (IG115300)

4-4 Register Files (3-States)



- **TC74HC4052AP** (IR405200)

Differential 4-Channel Multiplexer/Demultiplexer



- **TC4093BP** (IG043300)

Quad 2-Input NAND Schmitt Trigger



- **PCM56P** (XB637001)

Digital Analog Converter



- **M5238P** (XA013001)
- **RC4558D-V** (IG001390)
- **NJM4556** (IG042500)

Dual Operational Amplifier



■ ERROR MESSAGES

MIDI	
Display	**Error Message**
MIDI buffer full !	When the SY77 attempted to receive or transmit a large amount of MIDI data, its handling capacity was exceeded.
MIDI data error !	An error occurred when receiving MIDI data.
MIDI checksum err !	An error occurred when receiving bulk data.
Data empty !	There is no data to transmit.
Bulk rejected; song exist !	Since the selected song number already exists in sequencer memory, the sequence data (bulk) was not received. Select an unused song.
Song memory full !	When receiving sequence data (bulk), the internal memory capacity was exceeded, and not all the data was received.
Device number is off !	Since the device number is off, bulk data cannot be transmitted or received.
Device number mismatch !	Since the device numbers did not match, the bulk data was not received.
Bulk canceled by EXIT !	While receiving bulk data, EXIT was pressed to abort the operation.
Bulk protected !	Since the bulk protect is on, the bulk data was not received.

Data card	
Display	**Error Message**
Data card not ready !	The data card is not correctly inserted into the slot.
Card protected !	Since the memory protect switch of the card is on, data cannot be saved to the card.
Illegal formait !	The card is the wrong format.
Verify error !	The data was not correctly saved.

Wave card	
Display	**Error Message**
Wave card not ready !	The wave card is not correctly inserted into the slot.
Different wave card (ID =) !	The wave card which is inserted is not the one used by the voice or multi.
ID Number mismatch !	A multi includes voices which use two or more wave.

Disk	
Display	**Error Message**
Disk not ready !	The disk is not correctly inserted into the disk drive.
Illegal change !	During the backup operation, the original and back up disks were inserted in the wrong order.
Illegal disk !	The data in the disk is faulty.
Bad disk !	The disk is faulty.
File not found !	The file was not found.
Write protected !	The disk is write protected.
Disk full !	There is no more memory available on the disk.
Directory full !	The directory area on the disk is full, and new files cannot be created.
Media type error !	The disk is the wrong type.
Illegal file !	The file is not for the SY77.
Sequencer memory full !	The sequencer memory is full.

Sequencer and display	
Display	**Error Message**
Please stop sequencer !	The sequencer cannot play during disk or card loading or saving or during bulk data transmission.
Illegal time !	You attempted to execute the Get Pattern operation, but the time signature was incorrect.
Range is exceeded !	The parameter you specified in an edit job is beyond the valid range.
Data not Found !	When you executed the Search Part operation in Chain Pattern, the specified data was not found.
Illegal input !	You attempted to enter an invalid data value in Edit Insert mode.
Internal buffer full !	More sequence data was played back than could be sounded.

Battery	
Display	**Error Message**
Change internal battery !	The internal backup battery needs to be replaced.
Change card battery !	The card backup battery needs to be replaced.

Other	
Display	**Error Message**
Use bank D !	4 element voices can be stored (or copied) only to bank D.
Please stop sequencer !	Please stop the sequencer and try the operation once again.
Illegal mark !	You attempted to mark a display which does not allow marking.
Use bank A—C !	The voice must be stored in bank A, B, or C.

■エラーメッセージ

MIDI関係	
ディスプレイ表示	メッセージの内容
MIDI buffer full !	一度に多量のMIDIデータが送受信されたため、送受信ができません。データ量を減らしてください。
MIDI data error !	MIDIデータを受信した際、異常がありました。
MIDI checksum err !	バルクデータの受信の際、異常がありました。
Data empty !	シーケンスデータ(バルク)を送信しようとしましたが、データが内部にありません。
Bulk rejected; song exists !	現在選ばれているソング番号に、すでに別のデータが入っているため、シーケンスデータ(バルク)を受信できません。
Bulk canceled by EXIT !	シーケンスバルクデータ受信中にEXITが押されたので、データの受信を中止しました。シーケンスデータはクリアされた状態となります。
Song memory full !	シーケンスデータ(バルク)を受信した際、内部メモリーが一杯になってしまい、データを全て受信できません。
Bulk protected !	バルクプロテクトがオンになっているため、バルクデータの受信ができません。
Device number is off !	デバイスナンバーがオフになっているため、バルクデータの送受信ができません。
Device number mismatch !	デバイスナンバーのチャンネルが一致していないため、バルクデータの受信ができません。

データカード関係	
ディスプレイ表示	メッセージの内容
Data Card not ready !	カードが本体に正しくセットされていません。
Card protected !	カード自体のプロテクトスイッチがオンになっているため、データのセーブおよびオートストアができません。
Illegal format !	カードのフォーマットが違います。
Verify error !	カードのセーブが正しく行われていません。

ウェイブカード関係	
ディスプレイ表示	メッセージの内容
Wave card not ready !	ウェイブカードが本体に正しくセットされていません。
Different wave card (ID=) !	プレイしようとしているボイスで使用されるべきウェイブフォームは、現在カードスロットにセットされているものと異なるウェイブフォームカードのものです。
ID Number mismatch !	同時には、1つのウェイブフォームカードしか使用できないにも関わらず、マルチを構成する各々のボイスが必要とするウェイブフォームカードが異なるため、正常に発音しません。

ディスク関係	
ディスプレイ表示	メッセージの内容
Disk not ready !	ディスクが本体に正しくセットされていません。
Illegal change !	バックアップ作業中に、新旧のディスクの順番を間違って挿入しました。
Illegal disk !	ディスク内のデータ不良です。
Bad disk !	ディスク不良です。
File not found !	ファイルが見つかりません。
Write protected !	ディスクがプロテクトされています。
Disk full !	ディスクのメモリーが一杯です。
Directory full !	ディレクトリのエリアが一杯で、ファイルが作れません。
Media type error !	ディスクの種類が違います。
Illegal file !	本機用のファイルではありません。
Sequencer memory full !	シーケンス用の内部メモリーが一杯です。

シーケンサー関係	
ディスプレイ表示	メッセージの内容
Please stop sequencer !	ディスク、カードとのロード、セーブあるいは、バルクトランスミットなどは、シーケンサーがプレイされているときに実行することはできません。
Illegal time !	ゲットパターンを実行しようとしたが、設定されている拍子が異なっています。
Range is exceeded !	エディットジョブで指定したパラメータは設定できる範囲を超えています。
Data not Found !	チェインパターンでサーチパートを実行したが、目的のデータはありませんでした。
Illegal input !	エディットのインサートモードで入力しようとしたデータの値が正しくありません。
Internal buffer full !	シーケンサーを再生している時、シーケンスデータが多くて全てを発音することができません。

電池関係	
ディスプレイ表示	メッセージの内容
Change internal battery !	本体内のバックアップバッテリーが寿命です。
Change card battery !	カードのバックアップバッテリーが寿命です。

その他	
ディスプレイ表示	メッセージの内容
Use bank D !	4エレメントタイプのボイスは、バンクDにしかストアできません。 Disk 1 Voice loadの時、セーブ時にバンクDにあったボイスは、バンクDにしかロードできません。
Use bank A-C !	Disk 1 Voice loadの時、セーブ時にバンクA-Cにあったボイスは、バンクA-Cにしかロードできません。
Illegal mark !	現在の画面には、マークすることはできません。

■TEST PROGRAM

VERSION DISPLAY MODE

In order to verify the ROM versions of the SY77, you may want to initiate the Version Display Mode. To initiate this mode press and hold the [Voice], the [INTERNAL], and the [1] switches then the versions of the MAIN ROM and SEQUENCE (SEQ) ROM will be displayed. Press [EXIT] to return to the main program.

A. HOW TO ENTER THE TEST PROGRAM

Turn on the power switch of the SY77 and wait until the LCD has initialized and displays a normal operating mode message. While pressing the [VOICE] switch, press and hold the [BANK D] switch then the [8] switch. The SY77 will run the INITIAL TEST routine (refer to the INITIAL TEST section for details) and indicate that you have entered the Test Program by displaying the following message.

```
*** SY77 TEST Ver *.** *** Please Select

  Main ROM : Version *.*   1989-10-??
  SEQ. ROM : Version *.*   1989-10-??

    [-1] : AUTO          [+1] : MANUAL

  [COPY] : Fact.set    [EXIT] : Exit
```

Use the [−1], [+1], [COPY], or [EXIT] panel switches to select the appropriate test mode. If you press [−1], the auto test mode will be initiated. If you press [+1], the MANUAL test mode will be initiated. If you press [COPY], the SY77 will execute Test 48, "48. Factory settings", and then automatically exit the test mode and return to play mode (refer to Test 48 for details).
If you press [EXIT], you will exit the test mode and return to the play mode. The MANUAL mode is the preferred method of running the test program because it allows you to select or jump to any test and execute it. AUTO mode automatically executes each test in a fixed order. Some of the tests in the AUTO mode are automatically executed due to the nature of the test. In the AUTO mode simply press the [+1] switch to exit and automatically execute the next test or press [EXIT] to abort the test, then press [+1] to automatically execute the next test.

B. PROCEEDING THROUGH THE TESTS

(**MOST OF THESE FUNCTIONS MAINLY PERTAIN TO THE MANUAL TEST MODE**)
When you enter the test program, the following display will appear.

```
*** SY77 TEST Ver *.** *** MODE : MANUAL


 * 01 : ROM CHECK
   02 : RAM Read/Write
   03 : SEQENCER ROM
   04 : SEQENCER RAM
   05 : RAM Battery
```

Use the [+1], [−1], [ENTER], [COPY], [PAGE+], [PAGE−], [EXIT], or the numeric key pad, or the rotary encoder to move through the various tests of the test program.
Pressing: [+1] will execute the test which follows the current test.
[−1] will execute the test which precedes the current test.
[ENTER] will execute the currently selected test.
[PAGE+] will select the test which follows the current test and displays the test items.
[PAGE−] will select the test which precedes the current test and displays the test items.
[EXIT] will execute Test 49, "49. EXIT" (refer to Test 49 for details).

The numeric keys 0 through 9 of the entry pad can be used to enter a two-digit number to directly select a test. Simply enter the number and then press the [ENTER] switch. For example, if you would like to select TEST 6, press [0], [6] then press the [ENTER] switch.

TEST SELECTION WHEN AN ERROR IS DETECTED

In each of the following tests listed below, if an NG (No Good) error is detected, the following operations of the test will make the SY77 wait for the entry of a test number. You can then retry the test or perform another test. If you press [EXIT], the SY77 will wait for the entry of a test number.

9. Panel switches	10. Pitch bend	11. Modulation wheel 1
12. Modulation wheel 2	13. Data entry	14. Rotary encoder
15. Keyboard	16. Aftertouch	17. MIDI IN/OUT/THRU
18. Card insert	20. Card protect switch	22. Wave card insert
25. Disk eject	26. Breath controller	27. Foot volume
28. Foot controller	29. Sustain switch	30. Foot switch
47. Jacks all off		

INITIAL TEST

The following tests will be performed automatically when the test program is initiated.

A. Read/write check for the SRAM (IC130) work area of the DM1 circuit board.
B. Checks the interrupt levels of both M3 ICs (IC205 & IC228) of the DM2 circuit board.

DISPLAY OF TEST RESULTS

If each test checks OK then the Test program proceeds to the Tost Program entry display.
If Test A is NG the RAM WORK AREA may be at fault and the display will indicate:

```
** IC130(RAM) ERROR,TEST ABOARTED **
```

If Test B is NG then the error may be related to one of the M3 IC's IRQ levels.
The display will indicate the error by showing the following message:

```
* M3 IRQ CHECK ERROR,TEST ABOARTED *
```

EXITING THE TEST

This test automatically proceeds to the Test Program entry display if the items under test are OK.
If an error message occurs turn the power off and then on again to exit the test.
However, a RAM ERROR may not allow the SY77 to function normally.

TEST PROGRAM TEST 1–49 (MANUAL MODE OPERATION)

1. TEST 1: SYSTEM ROM TEST

```
* 01: ROM CHECK
```

Performs a read test on the ROM for the following addresses.

IC123 : 80000h–8000Fh IC124 : A0000h–A000Fh
IC125 : C0000h–C000Fh IC126 : E0000h–E000Fh
(This test checks only 16 bytes.)

DISPLAY OF TEST RESULTS

OK

```
* 01: ROM CHECK          4:IC126          OK
```

(the number of the last-tested IC)

or

NG

```
* 01: ROM CHECK          n:ICxxx          NG
```

(where n=ROM# and xxx=IC#)

TEST END

Ends after displaying the results.

2. TEST 2: SYSTEM RAM TEST

```
* 02: RAM Read/Write
```

Performs a read/write test of RAM on the following addresses.

IC127 : 40000h – 47FFFh IC128 : 48000h – 4FFFFh
IC129 : 50000h – 57FFFh IC130 : 58000h – 5FFFFh (Only 1024 bytes)

DISPLAY OF TEST RESULTS

OK

```
* 02: RAM Read/Write   4:IC130        OK
```

(the number of the last-tested IC)

or

NG

```
* 02: RAM Read/Write   n:ICxxx        NG
```

(where n = RAM # and xxx = IC #)

TEST END

Ends after displaying the results. All RAM data is preserved.

3. TEST 3: SEQUENCER ROM TEST

```
* 03: SEQENCER ROM
```

Performs a read test on the ROM (IC151) of DM1 circuit board.

DISPLAY OF TEST RESULTS

OK

```
* 03: SEQENCER ROM                   OK
```

NG

```
* 03: SEQENCER ROM                   NG
```

TEST END

Ends after displaying the results.

4. TEST 4: SEQUENCER RAM TEST

```
* 04: SEQENCER RAM
```

Performs a RAM read/write test on all addresses of IC153 (RAM 1), IC158 (RAM 2) and IC159 (RAM 3).

DISPLAY DF TEST RESULTS

OK

```
* 04: SEQENCER RAM   123             OK
```

NG

```
* 04: SEQENCER RAM   1x3             NG
```

(e.g. if RAM 2 is NG, an x will mark out the RAM 2 number indicating that it is no good.)

TEST END

Ends after displaying the results. All RAM data is preserved.

5. TEST 5: RAM BACKUP BATTERY TEST

This test checks that the voltage of the RAM backup battery is greater than 2.8V and less than 4.1V.

DISPLAY OF TEST RESULTS

OK



NG



TEST END

Ends after displaying the test results.

6. TEST 6: LCD – ALL DOTS "ON" TEST

Check that all dots of the LCD change to black (ON).

DISPLAY OF TEST RESULTS

First, the display indicates "* 06 LCD All On", then all dots of the LCD change to black (ON).

TEST END

Press [EXIT] to end the test. The display shown below will appear and the SY77 will wait for you to enter a test number.

7. TEST 7: LCD – ALL DOTS "OFF" TEST



Check that all dots change to white (OFF).

DISPLAY OF TEST RESULTS

First, the display indicates "* 06 LCD All OFF", then all dots of the LCD change to white (OFF).

TEST END

Press [EXIT] to end the test. The display shown below will appear and the SY77 will wait for you to enter a test number.



8. TEST 8: LED ON/OFF TEST

Check that each red LED blinks once in succession from the left end of the unit (refer to the diagram shown below) and then verify that all red LEDs blink together. Next, check that each green LED blinks once, and then all green LEDs blink together. The currently blinking LEDs will be displayed in the LCD as follows.

```
* 08: LED Check          REC  RED   On
```

(e.g. The red RECORD LED is blinking)

Check that all LEDs blink. (21 of the 32 LEDs are dual-color red/green LEDs)



Note: (◎) indicates a dual-color LED. (○) indicates a single-color LED.

TEST END

Press [EXIT] to end the test. The SY77 will then be waiting for the entry of a test number.

9. TEST 9: PANEL SWITCH TEST

```
* 09: Panel Switch
```

Press the panel switches consecutively from the [VOICE] switch to switch [16], according to the order indicated by the LCD display.

```
* 09: Panel Switch     Push REC
```

(e.g. When checking [RECORD])

The switch pressing order is displayed in the diagram below. If the switch is OK, a beep will sound and you should proceed to test the next switch. If the wrong switch is pressed an unexpected code is sent from the PKS CPU, and the error message NG will be displayed and no sound will be heard. At this time, if the correct switch is pressed then the proper code is received. You will then be able to proceed to test the next switch. The display will indicate OK, if all switches are good.



DISPLAY OF TEST RESULTS

OK

```
* 09: Panel Switch     Push 16          OK
```

NG

```
* 09: Panel Switch     Push REC  17 Err
```

TEST END
When switch [16] is pressed, OK is displayed and the test will end. During the test, if NG is detected, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

10. TEST 10: PITCH BEND WHEEL TEST

```
* 10: Pitch Bend      50      99
```

According to the target value displayed on the LCD, slowly move the pitch bend wheel. Check that the value changes from 50 to 99 then to 00 and back to 50 (in other words, center to top then to bottom and back to center).

```
* 10: Pitch Bend      xx      yy
```

(where xx = current pitch bend value and yy = next target value)

DISPLAY OF TEST RESULTS

OK
```
* 10: Pitch Bend      50      50      OK
```

NG
```
* 10: Pitch Bend      xx      Center  NG
```

(If the pitch bend value at the beginning or end of the test is not center, then xx indicates the pitch bend value when NG was detected).

TEST END
After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

11. TEST 11: MODULATIDN WHEEL 1 TEST

```
* 11: Modulation Whl 00      20-80
```

According to the target value displayed on the LCD, slowly move modulation wheel 1.
Check that the value changes from 00→20→80→99 then back down to 80→20→00 (in other words, from bottom to top the back to the bottom).

```
* 11: Modulation Whl  xx      yy
```

```
* 11: Modulation Whl  xx      yy-zz
```

(where xx = current value of modulation wheel 1, yy and zz are the next target values)

DISPLAY OF TEST RESULTS

OK
```
* 11: Modulation Whl  00      00      OK
```

NG (No change in display message)

TEST END
After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

12. TEST 12: MODULATION WHEEL 2 TEST

```
* 12: Modulation WH2  50      99
```

Before beginning this test, move modulation wheel 2 to the center position. According to the target value displayed on the LCD, slowly move modulation wheel 2. Check that the value changes from 50 to 99 then to 00 and back to 50 (in other words, from center to top then to bottom and back to center).

```
* 12: Modulation WH2  xx      yy
```

```
* 12: Modulation WH2  xx      yy-zz
```

(where xx = current value of modulation wheel 2, yy and zz are the next target values)

DISPLAY OF TEST RESULTS

OK

```
* 12: Modulation WH2  50      50      OK
```

NG (No change in display message)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

13. TEST 13: DATA ENTRY SLIDER TEST

```
* 13: Data Entry      00      20-80
```

According to the target value displayed on the LCD, slowly move the data entry slider. Check that the value changes from 00→20→80→99 and the back down to 80→20→00 (in other words, from the bottom to the top and back down to the bottom).

```
* 13: Data Entry      xx      yy
```

```
* 13: Data Entry      xx      yy-zz
```

(where xx = current value of data entry, yy and zz are the next target values)

DISPLAY OF TEST RESULTS

OK

```
* 13: Data Entry      00      00      OK
```

NG (No change in display message)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

14. TEST 14: RDTARY ENCDDER (DATA ENTRY WHEEL) TEST

```
* 14: R-Encoder        Right  00
```

Rotate the rotary encoder (deta entry wheel) to the right es indicated by the LCD display. Check that the value on the LCD changes from Right 00→Left 00→Left 01 (in other words, first rotate to the right then to the left).

```
* 14: R-Encoder        Right  xx
```

```
* 14: R-Encoder        Left   xx
```

(where xx = current value)

DISPLAY OF TEST RESULTS

OK

```
* 14: R-Encoder        Left   01      OK
```

NG (No change in display message)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

15. TEST 15: KEYBOARD TEST

```
* 15: Keyboard Check
```

Play a scale on the keyboard from C1 to C6 with a steady and even touch.

```
* 15: Keyboard Check  Push   C1
```

(e.g. in the case of C1)

If the key switch is ok, the note will sound and you should proceed to play the next key. If you play the wrong key this will produce an unexpected code to the PKS CPU and Err will be displayed. As a result the sound of that note will not be heard. However, if the right key is played following the playing of the wrong key, then correct code is received and the note for that key will sound. You can then proceed to play the next key. If all key switches are good then OK will be displayed on the LCD.

DISPLAY OF TEST RESULTS

OK

```
* 15: Keyboard Check  Push   C6      OK
```

NG

```
* 15: Keyboard Check  Push   xxx !7 Err
```

(if play the wrong key)

NG

```
* 15: Keyboard Check  Push   xxx $nn NG
```

(if the initial touch was incorrect)

TEST END

When you play the C6 key and OK is displayed, the test will end.
If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

16. TEST 16: AFTERTOUCH TEST

```
* 16: After Touch     00      20-80
```

According to the target value displayed on the LCD, press a key on the keyboard. Check that the value changes from 00→20→80→99 and back down to 80→20→00 (in other words, apply light pressure and increase pressure to a heavier touch then decrease back to a light touch).

```
* 16: After Touch     xx      yy
```

```
* 16: After Touch     xx      yy-zz
```

(where xx = the current aftertouch value, yy and zz are the next target values)

DISPLAY OF TEST RESULTS

OK
```
* 16: After Touch     00      00      OK
```

NG (No change in display message)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

17. TEST 17: MIDI TEST

```
* 17: MIDI (I/O/T)
```

After connecting the MIDI IN to the MIDI OUT via a MIDI cable, execute the test. The following message will appear on the LCD.

```
* 17: MIDI (I/O/T)     Tx:yy  Rx:zz
```

TEST END

When you press [EXIT] the test will end and the SY77 will wait for a test number to be entered. If an NG error occurs, because unexpected data was received, the test will end at that point. If an NG error occurs because no data was received within a certain time, the test will continue until [EXIT] is pressed.

18. TEST 18: DATA CARD INSERT TEST

```
* 18: D-Card Insert   0
```

Insert a RAM card (MCD64) into the DATA card slot and execute the test. Check that when you remove and insert the card back into the slot, the number on the display changes from 0 to 1 and that the OK result is displayed.

DISPLAY OF TEST RESULTS

OK
```
* 18: D-Card Insert   1                OK
```

NG (No change in display message)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

19. TEST 19: DATA CARDS READ/WRITE TEST

```
* 19: D-Card R/Write
```

This performs a read/write test on the following addresses of the RAM cards.
CARD 1 : 20000h – 27FFFh CARD 2 : 28000h – 2FFFFh
Insert a RAM cards with the memory protect turned off and execute the test.

DISPLAY OF TEST RESULTS

OK
```
* 19: D-Card R/Write  CARD : 12      OK
```

NG
```
* 19: D-Card R/Write  CARD :  x      NG
```
(e.g. if CARD 2 is No Good)

TEST END
After displaying the results, the test will end. All card data is preserved.

20. TEST 20: DATA CARD PROTECT SWITCH TEST

```
* 20: D-Card Protect  0
```

Use a RAM card to check that the card protect switch status is being read. Check that when the switch is set from "protect off" to "protect on", the number on the display changes from 0 to 1 and that the OK result is also displayed.

DISPLAY OF TEST RESULTS

OK
```
* 20: D-Card Protect  1              OK
```

NG (No change in display)

TEST END
After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

21. TEST 21: RAM BACKUP BATTERY TEST

```
* 21: D-Card Battery
```

This test checks that the voltage of the RAM card backup battery.

DISPLAY OF TEST RESULTS

OK
```
* 21: D-Card Battery  #.#V           OK
```

NG
```
* 21: D-Card Battery  #.#V   Low     NG
* 21: D-Card Battery  #.#V   High    NG
```

TEST END
Ends after displaying the test results.

22. TEST 22: WAVEFORM CARD INSERT TEST

```
* 22: W-Card Insert     0
```

Check that when a waveform card is inserted into the slot, the number on the display changes from 0 to 1 and that the OK result is displayed.

DISPLAY OF TEST RESULTS

OK

```
* 22: W-Card Insert     1                    OK
```

NG (No change in display)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

23. TEST 23: WAVEFORM CARD READ TEST

```
* 23: W-Card Read
```

This test is utilized by the factory and it is not intented for field service use.

24. TEST 24: DISK READ/WRITE TEST

```
* 24: Disk Read/Write
```

Use a blank disk to test the disk format. This test will write and read two types of data. Testing is performed on the following tracks.

SIDE 0 : TRACK 40 (sector 4)—TRACK 00 (sector 1)—TRACK 79 (sector 9)
SIDE 1 : TRACK 40 (sector 4)—TRACK 00 (sector 1)—TRACK 79 (sector 9)

Insert a blank disk with the write protect off and execute the test.

DISPLAY OF TEST RESULTS

OK

```
* 24: Disk Read/Write C79:H1 Verify  OK
```

NG

```
* 24: Disk Read/Write Cyy:Hx nnnnnnn NG
```

(where x = side or head number, yy = track or cylinder number, and nnnnnn: condition at time of error)

TEST END

After displaying the results, the test will end.

25. TEST 25: DISK EJECT TEST

```
* 25: Disk Eject       0
```

Insert a blank disk and execute the test. Check that when the eject button is pressed and the disk is removed, the number on the display changes from 0 to 1 and that the OK result is displayed.

DISPLAY OF TEST RESULTS

OK

```
* 25: Disk Eject      1              OK
```

NG (No change in display message)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

26. TEST 26: BREATH CONTROLLER TEST

```
* 26: Breath Control  99 00
```

Connect a breath controller and blow into it. Check that the number on the display changes from 00→01→20→80→95→99→80→20→01→00 (in other words, off to strong and back to off).

```
* 26: Breath Control  xx     yy-zz
```

(where xx = current breath control value, yy and zz are the next target values)

DISPLAY OF TEST RESULTS

OK

```
* 26: Breath Control  xx     00     OK
```

(where xx = breath controller value at end of test)

NG (No change in display)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

27. TEST 27: FOOT VOLUME TEST

```
* 27: Foot Volume     00     20-80
```

Connect a foot controller and operate it throughout its range. Check that the number on the display changes from 00→01→20→80→95→99→95→80→20→01→00 (in other words, starting from the raised position then to the lowered position and back to the raised position).

```
* 27: Foot Volume     xx     yy-zz
```

(where xx = current foot volume value, yy and zz are the next target values)

DISPLAY OF TEST RESULTS

OK

```
* 27: Foot Volume     xx     00     OK
```

(where xx = foot volume value at end of test)

NG (No change in display)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

28. TEST 28: FOOT CONTROLLER TEST

```
* 28: Foot Control      00      20-80
```

Connect a foot controller and operate it throughout its range. Check that the number on the display changes from 00→01→20→80→95→99→95→80→20→01→00 (in other words, starting from the raised position then to the lowered position and back to the raised position).

```
* 28: Foot Control      xx      yy-zz
```

(where xx=current foot controller value, yy and zz are the next target values)

DISPLAY OF TEST RESULTS

OK

```
* 28: Foot Control      xx      00      OK
```

(where xx=foot controller value at end of test)

NG (No change in display)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

29. TEST 29: SUSTAIN SWITCH TEST

```
* 29: Sustain          1
```

Connect a sustain switch and press it on and off. Check that the number on the display changes from 1 to 0 then back to 1 and verify that the OK result is displayed.

DISPLAY OF TEST RESULTS

OK

```
* 29: Sustain          1                 OK
```

NG (No change in display)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

30. TEST 30: FOOT SWITCH TEST

```
* 30: Foot Switch      1
```

Connect a foot switch and press it on and off. Check that the number on the display changes from 1 to 0 then back to 1 and verify that the OK result is displayed.

DISPLAY OF TEST RESULTS

OK

```
* 30: Foot Switch      1                 OK
```

NG (No change in display)

TEST END

After displaying the result, the test will end. If NG is detected during the test, refer to section B, "B. PROCEEDING THROUGH THE TESTS".

31. TEST 31: 1 kHz FM SOUND OUTPUT (OUTPUT L1) TEST

```
* 31: 1KHz to L1-> L1
```

Check that the correct signal is output from OUTPUT L1 and PHONES (L) jacks.
The signal route is as follows:
The digital representation of the 1 kHz signal is output from SOO terminal (channel 0) of OPS3 IC (IC251) to INDV1 terminal (channel 13) of the M3 IC (IC228). From the INDV1 terminal of the M3 IC, the signal sent to the IN1 terminal of the PAN(2) IC (IC230). From the PAN(2) IC, the signal is output from the S1 and S2 terminals. The signal is then sent to the MIX1 inputs of the MIX3 ICs (IC242 and IC243). Now the signal is sent out of the MIX3 ICs via the MXD terminals which feeds the signal to the SI1 and SI2 inputs of the AFDO (FLOATING POINT CONVERTER) IC. The AFDO and the DAC work together to produce the analog that is output from the CH1 (Channel 1) terminal. The signal goes to the analog circuits and is output from the OUTPUT L1 jack. It should be noted that the active low FMSEL signal must be at a 0 volt or LOW logic level in order to output this signal.

ITEMS TO CHECK

Insert the appropriate 1/4" phone plugs into each output jack and check OUTPUT L1, OUTPUT L2, OUTPUT R1, OUTPUT R2, and PHONES (L/R) outputs. If necessary, verify the frequency, output waveform, output level, and THD of each output using a frequency counter, oscilloscope, AC voltmeter (with 12.47 kHz filter) and distortion meter. The volume control must be set at maximum for these checks. While sounding, the LCD will display the following message:

```
* 31: 1KHz to L1-> L1  Output On
```

Listed below are the specifications and conditions of each output during this test.

OUTPUT L1 : 1kHz ± 1.5Hz, sine wave, distortion 0.2%, −1.0dB ± 2dB (10k ohm load)
OUTPUT L2 : less than −70dB
OUTPUT R1 : less than −70dB
OUTPUT R2 : less than −70dB
PHONES (L) : 1kHz, sine wave, distortion 0.2% or less, +5.0dB ± 2dB (150 ohm load)
PHONES (R) : less than −60dB

TEST END

Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 31: 1KHz to L1-> L1  Output Off
```

32. TEST 32: 1kHz FM SOUND OUTPUT (OUTPUT R1) TEST

```
* 32: 1KHz to R1-> R1
```

ITEMS TO CHECK

Check that the correct signal is output from OUTPUT R1 and the PHONES (R) jacks.
The basic signal route is the same as it was in TEST 31 except the signal is output from the CH2 (Channel 2) of the AFDO IC.
Insert the appropriate 1/4" phone plugs into each output jack and check OUTPUT L1, OUTPUT L2, OUTPUT R1, OUTPUT R2, and PHONES (L/R) outputs. If necessary, verify the frequency, output waveform, output level, and THD of each output using the previously specified test equipment (refer to TEST 31). The volume control must be set at maximum for these checks. While sounding, the LCD will display the following message:

```
* 32: 1KHz to R1-> R1  Output On
```

Listed below are the specifications and conditions of each output during this test.

OUTPUT R1 : 1kHz± 1.5Hz, sine wave, distortion 0.2%, −1.0dB± 2dB (10k ohm load)
OUTPUT R2 : less than −70dB
OUTPUT L1 : less than −70dB
OUTPUT L2 : less than −70dB
PHONES (L) : less than −60dB
PHONES (R) : 1kHz, sine wave, distortion 0.2% or less, +5.0dB± 2dB (150 ohm load)

TEST END

Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 32: 1KHz to R1-> R1  Output Off
```

33. TEST 33: 1kHz FM SOUND OUTPUT (OUTPUT L2) TEST

```
* 33: 1KHz to L2-> L2
```

ITEMS TO CHECK

Check that the correct signal is output from OUTPUT L2 and the PHONES (L) jacks.
The basic signal route is the same as it was in TEST 31 except the signal is output from the CH3 (Channel 3) of the AFDO IC.
Insert the appropriate 1/4" phone plugs into each output jack and check OUTPUT L1, OUTPUT L2, OUTPUT R1, OUTPUT R2, and PHONES (L/R) outputs. If necessary, verify the frequency, output waveform, output level, and THD of each output using the previously specified test equipment (refer to TEST 31). The volume control must be set at maximum for these checks. While sounding, the LCD will display the following message:

```
* 33: 1KHz to L2-> L2  Output On
```

Listed below are the specifications and conditions of the output during this test.

OUTPUT L2 : 1kHz± 1.5Hz, sine wave, distortion 0.2%, −1.0dB± 2dB (10k ohm load)
OUTPUT L1 : less than −70dB
OUTPUT R1 : less than −70dB
OUTPUT R2 : less than −70dB
PHONES (L) : 1kHz, sine wave, distortion 0.2% or less, +5.0dB± 2dB (150 ohm load)

TEST END

Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 33: 1KHz to L2-> L2  Output Off
```

34. TEST 34: 1kHz FM SOUND OUTPUT (OUTPUT R2) TEST

```
* 34: 1KHz to R2-> R2
```

ITEMS TO CHECK

Check that the correct signal is output from OUTPUT R2 and the PHONES (R) jacks.
The basic signal route is the same as it was in TEST 31 except the signal is output from the CH4 (Channel 4) of the AFDO IC.
Insert the appropriate 1/4" phone plugs into each output jack and check OUTPUT L1, OUTPUT L2, OUTPUT R1, OUTPUT R2, and PHONES (L/R) outputs. If necessary, verify the frequency, output waveform, output level, and THD of each output using the previously specifled test equipment (refer

to TEST 31). The volume control must be set at maximum for these checks. While sounding, the LCD will display the following message:

```
* 34: 1KHz to R2-> R2  Output On
```

Listed below are the specifications and conditions of each output during this test.

OUTPUT R2 : 1kHz ± 1.5Hz, sine wave, distortion 0.2%, −1.0dB ± 2dB (10k ohm load)
OUTPUT R1 : less than −70dB
OUTPUT L1 : less than −70dB
OUTPUT L2 : less than −70dB
PHONES (R) : 1kHz, sine wave, distortion 0.2% or less, +5.0dB ± 2dB (150 ohm load)

TEST END

Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 34: 1KHz to R2-> R2  Output Off
```

35. TEST 35: 1kHz FM SOUND OUTPUT (OUTPUT L2 OUTPUT L1) TEST

```
* 35: 1KHz to L2-> L1
```

ITEMS TO CHECK

Check that when the plug connected to OUTPUT L2 is pulled out, the signal being output from OUTPUT L2 is now output from OUTPUT L1. The basic signal route is the same as it was for TEST 33.
Insert the appropriate 1/4" phone plug into OUTPUT L1 and verify, if necessary, the frequency, output waveform, output level, and THD of this output using the previously specified test equipment (refer to TEST 31). The volume control must be set at maximum for this test. While sounding, the LCD will display the following message:

```
* 35: 1KHz to L2-> L1  Output On
```

The specifications for this test are as follows:

OUTPUT L1 : 1kHz, sine wave, −1.0dB ± 2dB (10k ohm load)

TEST END

Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 35: 1KHz to L2-> L1  Output Off
```

36. TEST 36: 1kHz FM SOUND OUTPUT (OUTPUT R2 OUTPUT R1) TEST

```
* 36: 1KHz to R2-> R1
```

ITEMS TO CHECK

Check that when the plug connected to OUTPUT R2 is pulled out, the signal being output from OUTPUT R2 is now output from OUTPUT R1. The basic signal route is the same as it was for TEST 34.
Insert the appropriate 1/4" phone plug into OUTPUT R1 and verify, if necessary, the frequency, output waveform, output level, and THD of this output using the previously specified test equipment (refer to TEST 31). The volume control must be set at maximum for this test. While sounding, the LCD will display the following message:

```
* 36: 1KHz to R2-> R1  Output Off
```

The specifications for this test are as follows:
OUTPUT R1 : 1kHz, sine wave, −1.0dB±2dB (10k ohm load)

TEST END
Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.,

```
* 36: 1KHz to R2-> R1  Output Off
```

37. TEST 37: 1kHz FM SOUND OUTPUT (OUTPUT R1→OUTPUT L1) TEST

```
* 37: 1KHz to R1-> L1
```

ITEMS TO CHECK
Check that when the plug connected to OUTPUT R1 is pulled out, the signal being output from OUTPUT R1 is now output from OUTPUT L1. The basic signal route is the same as it was for TEST 32.
Insert the appropriate 1/4" phone plug into OUTPUT L1 and verify, if necessary, the frequency, output waveform, output level, and THD of this output using the previously specified test equipment (refer to TEST 31). The volume control must be set at maximum for this test. While sounding, the LCD will display the following message:

```
* 37: 1KHz to R1-> L1  Output On
```

The specifications for this test are as follows:
OUTPUT L1 : 1kHz, sine wave, −1.0dB±2dB (10k ohm load)

TEST END
Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 37: 1KHz to R1-> L1  Output Off
```

38. TEST 38: 1kHz FM SOUND OUTPUT (EFFECT 0→OUTPUT L1) TEST

```
* 38: Effect_0 to L1
```

ITEMS TO CHECK
The basic signal route is the same as it was for TEST 31 except that the signal is sent out of CH1 through CH4 (Channels 1−4). In other words, a signal is output to OUTPUT L1, OUTPUT L2, OUTPUT R1 and OUTPUT R2. With no 1/4" phone plugs inserted, the signals from these outputs will all be sent to OUTPUT L1.
Insert the appropriate 1/4" phone plug into OUTPUT L1 only and verify, if necessary, the frequency, output waveform, output level, and THD of this output using the previously specified test equipment (refer to TEST 31).
The volume control must be set at maximum for this test. While sounding, the LCD will display the following message:

```
* 38: Effect_0 to L1     Output On
```

The specifications for this test are as follows:
OUTPUT L1 : 1kHz, sine wave, distortion 0.3% or less, +11.0dB±2dB (10k ohm load)

TEST END
Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 38: Effect_0 to L1   Output Off
```

39. TEST 39: 1kHz FM SOUND OUTPUT (EFFECT 1→OUTPUT L1) TEST

```
* 39: Effect_1 to  L1
```


There are two signal paths for this test. The basic signal path is the same as it was for TEST 31 except for the following:

SIGNAL PATH 1
The signal from the PAN IC is input to pin 2 (SI0 terminal) of the LEF (1) IC (IC232) via pin 9 of IC254. The signal is then output from pin 4 (SO0 terminal) of the LEE (1) IC to pin 10 (SI0 terminal) of the LDSP (1) IC (IC236).
The LDSP(1) IC outputs the signal via pin 33 (SO0 terminal) to pin 2 (MIX2 terminal) of MIX3 (1) IC (IC242). This ultimately produces signal output from OUTPUT L1 and OUTPUT R1.

SIGNAL PATH 2
The signal from the PAN IC is input to pin 2 (SI0 terminal) of the LEF (2) IC (IC233) via pin 19 of IC254. The signal is then output from pin 4 (SO0 terminal) of the LEF (2) IC to pin 10 (SI0 terminal) of the LDSP (2) IC (IC237). The LDSP (2) IC outputs the signal via pin 33 (SO0 terminal) to pin 2 (MIX2 terminal) of MIX3 (2) IC (IC243). This ultimately produces signal output from OUTPUT L2 and OUTPUT R2.
It should be noted that the LEF ICs use their associated DRAM ICs and the LDSP ICs use their associated PSRAM to process the signals for this test.

ITEMS TO CHECK
Insert the appropriate 1/4" phone plug into OUTPUT L1 only and verify, if necessary, the frequency, output waveform, output level, and THD of this output using the previously specified test equipment (refer to TEST 31). The volume control must be set at maximum for this test.
While sounding, the LCD will display the following message:

```
* 39: Effect_1 to  L1  Output On
```

The specifications for this test are as follows:
OUTPUT L1 : 1kHz, sine wave, distortion 0.3% or less, +11.0dB±2dB (10k ohm load)

TEST END
Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 39: Effect_1 to  L1  Output Off
```

40. TEST 40: 1kHz FM SOUND OUTPUT (EFFECT 2→OUTPUT L1) TEST

```
* 40: Effect-2 to  L1
```

There are two signal paths for this test. The basic signal path is the same as it was for TEST 31 except for the following:

SIGNAL PATH 1
The signal from the PAN IC is input to pin 2 (SI0 terminal) of the LEF (2) IC (IC233) via pin 19 of IC254. The signal is then output from pin 4 (SO0 terminal) of the LEF (2) IC to pin 11 (SI1 terminal) of the LDSP (1) IC (IC236). The LDSP (1) IC outputs the signal via pin 33 (SO0 terminal) to pin

11 (SI1 terminal) of the LDSP (2) IC (IC237). From the LDSP (2) IC, pin 33 (SO0 terminal), the signal is output to pin 3 (MIX3 terminal) of MIX3 (1) IC (IC242). This ultimately produces signal output from OUTPUT L1 and OUTPUT R1.

SIGNAL PATH 2
The signal from the PAN IC is input to pin 2 (SI0 terminal) of the LEF (2) IC (IC233) via pin 19 of IC254. The signal is then output from pin 5 (SO1 terminal) of the LEF (2) IC to pin 4 (MIX4 terminal) of MIX3 (2) IC (IC243). This ultimately produces signal output from OUTPUT L2 and OUTPUT R2.
It should be noted that the LEF ICs use their associated DRAM ICs and the LDSP ICs use their associated PSRAM to process the signals for this test.

ITEMS TO CHECK
Insert the appropriate 1/4" phone plug into OUTPUT L1 only and verify, if necessary, the frequency, output waveform, output level, and THD of this output using the previously specified test equipment (refer to TEST 31). The volume control must be set at maximum for this test.
While sounding, the LCD will display the following message:

```
* 40: Effect-2 to  L1  Output On
```

The specifications for this test are as follows:
OUTPUT L1 : 1kHz, sine wave, distortion 0.3% or less, +10.0dB±2dB (10k ohm load)

TEST END
Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 40: Effect-2 to  L1  Output Off
```

41. TEST 41: AWM (M3) SOUND OUTPUT TEST

```
* 41: PCM Check
```

SIGNAL PATH
This outputs the sound which is stored in addresses 012000h–01FFFFh of WAVE ROM. The data stored at these addresses is retrieved by the M3(A) IC (IC205) and output via pin 1 (INDV0 terminal, channel 0). The signal from pin 1 is then output to pin 11 (IN0 terminal) of the PAN(1) IC (IC229). The PAN (1) IC outputs the signal from pins 21 and 22 (S1 and S2 terminals, respectively) and sends the signal to pins 12 and 13 (SI2 and SI1 terminals, respectively) of the PAN (2) IC (IC230). The PAN (2) IC outputs the signal from pins 21 and 22 (S1 and S2 terminals, respectively) to pin 1 (MIX1 terminal) of each MIX3 IC. This ultimately produces signal output from OUTPUT L1, OUTPUT R1, OUTPUT L2, OUTPUT R2.

ITEMS TO CHECK
Confirm that a AWM signal is being sent to OUTPUT L1 using an amplifier and speaker to monitor the signal. The AWM signal is not a steady tone. While this signal is sounding, the LCD will display the following message:

```
* 41: PCM Check          Output On
```

TEST END
Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 41: PCM Check          Output Off
```

42. TEST 42: FM SOUND OUTPUT THROUGH M3 IC (AWM) TEST

```
* 42: FM Thru M3(PCM)
```

SIGNAL PATH
A sine wave which is frequency swept by the EGM2 (1) IC will cause signals to be alternately output from OUTPUT L1, OUTPUT R1, OUTPUT L2 and OUTPUT R2 in a two channel pair sequence. The FMSEL signal to the EGM2 (1) and OPS3 (1) must be at a 1 or HIGH logic level for this test. The appropriate data from EGM2 (1) IC (IC226) is sent to the OPS3 (1) IC (IC227) In order to produce the sound. The OPS3 (1) IC outputs the signals from pins 54 and 55 (SO0, channel 1 and SO1, channel 9) via IC252 (pins 3 and 6) to pins 27 and 28 (terminals DIIN0 and DIIN1) of the M3 (A) IC (IC205). The M3 (A) IC outputs the signals from pins 1 and 2 (INDV0, channel 5 and INDV1, channel 6) to pins 10 and 11 (IN1 and IN0 terminals) of the PAN (1) IC (IC229). The PAN (1) IC sends the signals out from pins 21 and 22 (S1 and S2 terminals) to pins 12 and 13 (SI2 and SI1 terminals) of the PAN (2) IC (IC230). The PAN (2) IC outputs the signals from pins 21 and 22 (S1 and S2 terminals) to pin 1 (MIX1 terminal) of each MIX3 IC. This ultimately produces signal output from OUTPUT L1, OUTPUT R1, OUTPUT L2, OUTPUT R2.

ITEMS TO CHECK
Insert the appropriate 1/4" phone plug into OUTPUT L1 and observe the output waveform with an oscilloscope. Check that the level does not change excessively as the output sweeps through its frequency range. The volume control must be set at comfortable listening level for this test. While sounding, the LCD will display the following message.

```
* 42: FM Thru M3(PCM)  Output On
```

TEST END
Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 42: FM Thru M3(PCM)  Output Off
```

43. TEST 43: FM SOUND OUTPUT THROUGH M3 IC (DIGITAL FILTER) TEST

```
* 43: FM Thru M3(FM)
```

SIGNAL PATH
A sine wave which is frequency swept by the EGM2 (2) IC will cause signals to be alternately output from OUTPUT L1, OUTPUT R1, OUTPUT L2 and OUTPUT R2 in a two channel pair sequence. The FMSEL signal to the EGM2 (2) and OPS3 (2) must be at a 0 or LOW logic level for this test. The appropriate data from EGM2 (2) IC (IC250) is sent to the OPS3 (2) IC (IC251) in order to produce the sound. The OPS3 (2) IC outputs the signals from pins 54 and 55 (SO0, channel 0 and SO1, channel 8) via IC252 (pins 3 and 6) to pins 27 and 28 (terminals DIIN0 and DIIN1) of the M3 (B) IC (IC228). The M3 (B) IC outputs the signals from pins 1 and 2 (INDV0, channel 14 and INDV1, channel 15) to pins 10 and 11 (IN1 and IN0 terminals) of the PAN (2) IC (IC230). The PAN (2) IC sends the signals out from pins 21 and 22 (S1 and S2 terminals) to pin 1 (MIX1 terminal) of each MIX3 IC. This ultimately produces signal output from OUTPUT L1, OUTPUT R1, OUTPUT L2, OUTPUT R2.

ITEMS TO CHECK
Insert the appropriate 1/4" phone plug into OUTPUT L1 and observe the output waveform with an oscilloscope. Check that the level does not change excessively as the output sweeps through its frequency range. The volume control must be set at a comfortable listening level for this test. While sounding, the LCD will display the following message.

```
* 43: FM Thru M3(FM)  Output On
```

TEST END
Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 43: FM Thru M3(FM)  Output Off
```

44. TEST 44: FM SOUND OUTPUT FEEDBACK THROUGH M3 IC TEST

```
* 44: Feedback FM->M3
```

The basic signal path is the same as it was for TEST 42 except for the following:
The frequency swept sine wave produced by the EGM2 (1) and OPS3 (1) will be fed back from the M3 (A) IC to the OPS3 (1) IC. As in TEST 42, the output signals will occur alternately in a two channel pair sequence. For this test, the signals from pins 1 and 2 (INDV0 and INDV1 terminals) of M3 (A) IC (IC205) will be fed back to pins 69 and 70 (SI0 and SI1 terminals) of OPS3 (1) IC (IC227).

ITEMS TD CHECK
Insert the appropriate 1/4" phone plug into OUTPUT L1 and observe the output waveform with an oscilloscope. Check that the level does not change excessively as the output sweeps through its frequency range. It should be noted that due to the feedback condition of this test there may be a slight amount of distortion present in the output signal. The volume control must be set at a comfortable listening level for this test. While sounding, the LCD will display the following message:

```
* 44: Feedback FM->M3  Output On
```

TEST END
Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 44: Feedback FM      Output Off
```

45. TEST 45: HIGH CLICK SOUND TEST

```
* 45: Click High
```

ITEMS TO CHECK
Check that a high click signal is properly output from OUTPUT L1, OUTPUT L2, OUTPUT R1 and OUTPUT R2. Make sure that the click volume control is set to maximum. While sounding, the LCD will display the following message:

```
* 45: Click High      Click On
```

Verify that the high click signal is sent to each output by using an amplifier and speaker to monitor signal. Insert the appropriate 1/4" phone plugs into OUTPUT L1, OUTPUT L2, OUTPUT R1 and OUTPUT R2 and observe the output waveform with an oscilloscope. Check that the output waveform is a rounded square wave with an approximate peak-to-peak voltage of 500mV.

TEST END
Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 45: Click High      Click Off
```

46. TEST 46: LOW CLICK SOUND TEST

```
* 46: Click Low
```

ITEMS TO CHECK

Check that a low click signal is properly output from OUTPUT L1. Make sure that the click volume control is set to maximum. While sounding, the LCD will display the following message:

```
* 46: Click Low      Click On
```

Verify that the low click signal is sent to OUTPUT L1 by using an amplifier and speaker to monitor signal. Insert the appropriate 1/4" phone plugs into OUTPUT L1, OUTPUT L2, OUTPUT R1 and OUTPUT R2 and observe the output waveform with an oscilloscope. Check that the output waveform is a rounded square wave with an approximate peak-to-peak voltage of 500mV.

TEST END

Press [EXIT] to end the test. After pressing [EXIT] three things occur;
(1) the following display will appear, (2) the sound will stop and (3) the SY77 will wait for the entry of a test number.

```
* 46: Click Low      Click Off
```

47. TEST 47: JACKS ALL OFF TEST

```
* 47: Jack All Off
```

Connect the Sustain and Foot Switch pedals to the appropriate jacks. With nothing connected to the Foot Volume, Foot Controller, and Breath controller jacks, check that the following display appears.

```
* 47: Jack All Off          SU FS
```

Then while pressing the foot switches connected to the Sustain and Foot Switch jacks, remove the pedal plugs, and check that the display shows "OK".

DISPLAY OF TEST RESULTS

OK

```
* 47: Jack All Off                    OK
```

NG

```
* 47: Jack All Off    FV              NG
```

(e.g. if the foot volume jack is NG)

TEST END

The result is displayed and the test will end.

48. TEST 48: FACTORY SET TEST

```
* 48: Factory Set
```

This test is used to initialize the data listed below to the factory settings:

Synthesizer system data
64-internal voice data
16-internal multi data
Sequencer setup data

When this test is executed, the following display will appear.

```
* 48: Factory Set    [NO] or [YES] ?
```

If you press [YES], the factory preset data will be restored.
If you press [NO], they will not be restored.

DISPLAY OF TEST RESULTS

If factory settings are restored.

OK

```
* 48: Factory Set                    OK
```

If not restored there will be no change in the display as shown below.

```
* 48: Factory Set     [NO] or [YES] ?
```

TEST END

The LCD displays the results, the factory preset data will be restored, and the test will then end.
After the factory preset data has been restored, the system data will be as follows:

```
**********************
*       SYNTH        *
**********************
```

Note Shift·····+0
Fine Turning ·····+0
Fixed Velocity·····off
Velocity Curve ·····0(normal)
Assignable Foot Switch ·····65
Assignable Wheel ·····13
Edit Confirm ·····on
Kbd Trans Ch·····1
Voice Recv Ch·····omn
Local on/off·····on
Note on/off ·····all
Device Number ·····all
Bulk Protect ·····on
Program Change·····normal

---------- Greeting Message ----------

"Create YOUR sound ! "
" ...I'm ready"

---------- PAN factory set ----------

11~132 = P1 ~P32

---------- MCT factory set ----------

1 1 = P62(Far East)
1 2 = P63(Blue)

--------- VOICE --------- ---------

I-A01~D16 =P1-A01~D16

--------- MULTI --------- ---------

I-A01~D16 =P1-A01~D16

```
************************
*     SEQUENCER        *
************************
```

record quantize ·····0(off)
click sw·····1(rec)
click beat ·····0(1/4)

record type ·····over
sync ·····0(internal)
receive ·····KBD

filter velocity ·····1(on)
filter control change ·····1(on)
filter pitch bend ·····1(on)
filter program change ·····0(off)
filter after touch·····0(off)
filter exclusive ·····1(on)

midi control·····1(on)
click/beat·····1/96

accent 1 value ·····24
accent 2 value ·····56
accent 3 value ·····88
accent 4 value ·····120
gate type ·····1(normal)

49. TEST 49: EXIT TEST PROGRAM

```
* 49: Exit
```

When this is executed, the following display will appear.

```
* 49: Exit              [NO] or [YES] ?
```

To exit the test program mode, press the [YES] switch. To remain in the test program mode press the [NO] switch. This will cause the SY77 to wait for the entry of a test number.

DISPLAY OF TEST RESULTS
If test mode is not exited.

```
* 49: Exit              [NO] or [YES] ?
```

MUSIC SYNTHESIZER

SY77

PARTS LIST

Notes DESTINATION ABBREVIATIONS

J : Japanese model	A : Australian model
U : U.S. model	E : European model
C : Canadian model	D : West German model
X : General model	B : British model
M : South African model	I : Indonesian model
H : North European model	

■ELECTRICAL PARTS（電気部品）

Ref. No.	Part No.	Description		部品名	Remarks	ランク
	VH799000	Circuit Board	DMI	DMIシート		
	VH799100	Circuit Board	DM2	DM2シート		
	VH799200	Circuit Board	PNAB	PNABシート		
	VH799400	Circuit Board	PNC	PNCシート		
	NX808420	Circuit Board	JKAN	JKANシート		
	NX808430	Circuit Board	CARD	CARDシート		
	NAJ15670	Circuit Board	MK	MKシート		09
	NAJ09720	Circuit Board	PC	PCシート		07
	VH799600	Circuit Board	PS	PSシート	J	
	VH799700	Circuit Board	PS	PSシート	H,C	
	VH799800	Circuit Board	PS	PSシート	B,D,A,8	
	VH799000	Circuit Board	DMI	DMIシート		
	IG001390	IC	RC4558D-V	IC	OP AMP.	03
	IG110200	IC	PST518B-Z	IC	SYSTEM RESET	04
	IG063690	IC	74F00PC	IC	NAND	04
	IR000250	IC	SN74HC02N	IC	NOR	03
	IG027020	IC	SN74LS04N	IC	INVERTER	04
	IG142250	IC	SN74HCU04N	IC	INVERTER	01
	XC723001	IC	SN74HCU04NSR	IC	INV. S/#PZ1001-	03
	XA870001	IC	SN74ALS08N	IC	AND	03
	IR001450	IC	SN74HC14N	IC	INVERTER	05
	IG058990	IC	74F32PC	IC	OR	04
	IR003250	IC	SN74HC32N	IC	OR	03
	XA055001	IC	SN74ALS32N	IC	OR	03
	IR007450	IC	SN74HC74N	IC	D-FF	04
	XA196A00	IC	SN74ALS74N	IC	FF	02
	IG120090	IC	74F138PC	IC	3-8DECODER	06
	IG149600	IC	SN74ALS138N	IC	DECODER	04
	IR013850	IC	SN74HC138N	IC	3-8DECODER	05
	IG149900	IC	SN74ALS245AN	IC	BUS TRANSCEIVER	07
	IR024500	IC	TC74HC245P	IC	BUS BUFFER	07
	IG115300	IC	MD74LS670P	IC	REGISTER FILE	05
	IR405200	IC	TC74HC4052AP	IC	DEMULTIPLEXER	03
	XF148A00	IC	MD63C01Y0F64P	IC	SEQ. CPU	09
	XG044800	IC	MD6475328CP-10	IC	MAIN CPU H8/532	
	XG050B00	IC	MD637B01Y	IC	CPU-PKS	
	XB361001	IC	μPD71055C	IC	PPI	06
	XH129A00	IC	MD37C65B-JH00	IC	FDC	10
	XF870A00	IC	LH5164D-10L	IC	SRAM 64K	08
	XF863A00	IC	μPD43256AC-12L	IC	SRAM 256K	13
	XG708A00	IC	HM62256LP-12	IC	SRAM 256K	18
	XG9G0A00	IC	TC55257BPL-10	IC	SRAM 256K	13
	XC628A00	IC	TC51832PL-10	IC	PSRAM 256K	09
	XH110A00	IC	HM65256BLP-10	IC	PSRAM 256K	09
	XH118B00	IC	101AV100 120nsec	IC	EPROM V1.00	
	XH119B00	IC	101BV100 120nsec	IC	EPROM V1.00	
	XH120B00	IC	101CV100 120nsec	IC	EPROM V1.00	
	XH121B00	IC	101DV100 120nsec	IC	EPROM V1.00	
	XH122B00	IC	101EV100 120nsec	IC	EPROM V1.00	
	IA101521	Transistor	2SA1015 Y	トランジスタ		03
	IC181520	Transistor	2SC1815 Y	トランジスタ		03
	ID003450	Diode	1SS133	ダイオード		01
	VI546800	Zener Diode	RD3.0ESB1 3V	ツェナーダイオード		01
	UJ838470	Electrolytic Cap.	470μ 16V M	ケミコン		01
	ED736470	Tantalum Capacitor	4.7μ 16V M	タンタルコン		01
	VC694800	Semiconductive Cera. Cap.	0.1μ 25V Z	半導体セラコン		01
	VC824900	Metal Film Resistor	10KΩ 1/8W F	金属被膜抵抗		01
	NZ004050	Resistor Array	RMLS08J103	抵抗アレイ		02
	VA822600	Resistor Array	RMLS04J103	抵抗アレイ		01
	VE445200	Resistor Array	RGLD8X103J	抵抗アレイ		01
	VE445300	Resistor Array	RGLD8X153J	抵抗アレイ		01
	VE445400	Resistor Array	RGKD8X223J	抵抗アレイ		01
	VJ035300	Resistor Array	RMLS6-221J	抵抗アレイ		01
	PZ000070	EMI Filter	LS MT Y223NB	LCフィルターEMI		02
	VE4B3500	Quartz Crystal Unit	AT-49 12MHz	水晶振動子		03
	VI927300	Quartz Crystal Unit	AT-49 20MHz	水晶振動子		03
	VI927400	Quartz Crystal Unit	DOC-492 16MHz	水晶振動子	S/# PY1001-2220	07
	VI573400	Quartz Crystal Unit	AT-49 16MHz	水晶振動子	S/# PZ1001-	03
	VR338400	Lithium Battery	SONY/CR2032	リチュウム電池		03
	VH930600	Angle Bracket,Earth		アース金具		01
	VH799100	Circuit Board	DM2	DM2シート		
	XD830A00	IC	SN74HC04NSR	IC	INVERTER	01
	IG049850	IC	SN74LS32N	IC	OR	03

*New Parts（新規部品）

ランク：Japan only

Ref. No.	Part No.	Description		部品名	Remarks	ランク
	IR013950	IC	SN74HC139N	IC	2-4DECODER	05
	IG044600	IC	SN74LS245	IC	TRANSCEIVER	08
	IG149900	IC	SN74ALS245AN	IC	BUS TRANSCEIVER	07
	IR024550	IC	SN74HC245N	IC	TRANSCEIVER	06
	IR027350	IC	SN74HC273N	IC	D-FF OCTAL	05
	IR035750	IC	SN74HC367N	IC	BUS DRIVER	06
	IG150010	IC		IC	MIX3	05
	XE449A00	IC	YM3413	IC	LDSP	10
	XE450A00	IC	YM3415	IC	LEF	12
	XG990A00	IC	YM7102	IC	PAN	10
	XG993A00	IC	YM7103	IC	EGN2	13
	XG994A00	IC	YM7107	IC	OPS3	13
	XG995A00	IC	YM7110	IC	M3	18
	XD281A00	IC	LM2464-12	IC	DRAM 256K	08
	XC828A00	IC	TC51832PL-10	IC	PSRAM 256K	09
	XH116A00	IC	HM65256BLP-10	IC	PSRAM 256K	09
	XH024B00	IC	MN62304BPH28	IC	ROM-A 4M	16
	XH025B00	IC	MN62304BPH29	IC	ROM-B 4M	16
	XH026B00	IC	MN62304BPH30	IC	ROM-C 4M	16
	XH027B00	IC	MN62304BPH31	IC	ROM-D 4M	16
*	XH028B00	IC	MN62304BPH32	IC	ROM-E 4M	16
*	XH029B00	IC	MN62304BPH33	IC	ROM-F 4M	16
*	XH030B00	IC	MN62304BPH34	IC	ROM-G 4M	16
*	XH031B00	IC	MN62304BPH35	IC	ROM-H 4M	16
	VC694800	Semiconductive Cera. Cap.	0.1μ 25V Z	半導体セラコン		01
	VE443500	Resistor Array	RGLD4X103J	抵抗アレイ		01
	VE445200	Resistor Array	RGLD8X103J	抵抗アレイ		01
	FZ006970	EMI Filter	LS MT Y223MB	LCフィルターEMI		02
*	VH949900	Quartz Crystal Unit	AT-49 6.144MHz	水晶振動子		03
*	VH930600	Angle Bracket,Earth		アース金具		01
*	VH799200	Circuit Board	PNAB	PNABシート		
	IA101521	Transistor	2SA1015 Y	トランジスタ		03
	VG197400	LED	GL3HD18 RE	LED	MTI,BYPASS,RECO	01
	VG197600	LED	GL3ED8 RE+GR	2色LED	MODE,RUN (5pcs)	01
	VE373500	Slide Pot.	A10K×2	二連スライドボリウム	VOL.(OUTPUT1,2)	03
	VF946200	Push Switch	SOA-1111HS	プッシュスイッチ	(25pcs)	01
*	VH812000	LED Spacer	×8	LEDスペーサー	LED1-6	02
*	VH812100	LED Spacer	×4	LEDスペーサー	LED7,8	01
*	VH799400	Circuit Board	PNC	PNCシート		
	IR027350	IC	SN74HC273N	IC	D-FF OCTAL	05
	IF003450	Diode	1SS133	ダイオード		01
	VG197400	LED	GL3HD18 RE	LED	MEMORY,BANK(8pc	01
	VG197600	LED	GL3ED8 RE+GR	2色LED	Voice sel.1-16	01
	VC694800	Semiconductive Cera. Cap	0.1μ 25V Z	半導体セラコン		01
	VC250600	Slide Pot.	B10K GWA-NFOC	スライドボリウム	DATA ENTRY	03
	VB436400	Rotary Switch	EC24B30D	ロータリースイッチ	Data entry Dial	07
	VF946200	Push Switch	SOA-1111HS	プッシュスイッチ	(45pcs)	01
*	VH812000	LED Spacer	×8	LEDスペーサー		02
*	HX808420	Circuit Board	JKAN	JKANシート		
	IG001390	IC	RC4558D-V	IC	OP AMP.	03
	IG042500	IC	NJM4556	IC	OP AMP.	04
	XA013001	IC	M5238P	IC	OP AMP.	04
	IG130500	IC	NJM79L05	IC	REGULATOR -5V	03
	XC349001	IC	μPC78L05J	IC	REGULATOR +5V	02
	IG043300	IC	TC4093BP	IC	NAND	05
	IG052600	IC	HD74LS05P	IC	INVERTER	03
	XB037001	IC	PCM56P	IC	DA CONVERTER	09
	XF237A00	IC	YM3029	IC	AFDC	09
	VD473200	Photo Coupler	6N137	フォトカプラ		05
	IA111510	Transistor	2SA1115 E,F	トランジスタ		03
	IC094530	Transistor	2SC945A PA	トランジスタ		03
	IC260320	Transistor	2SC2603 E,F	トランジスタ		03
	IC287820	Transistor	2SC2878 A,B	トランジスタ		03
	IF003450	Diode	1SS133	ダイオード		01
	VC694800	Semiconductive Cera. Cap.	0.1μ 25V Z	半導体セラコン		01
	VG582600	DC/AC Inverter Transformer	D32-49	DC/ACインバータトランス		07
	VB835000	Coil	20μH FL5R200QN	コイル		01
	VD048800	Variable Resistor	A10K EVU-E	ロータリーボリウム	CLICK VOLUME	02
	VI573700	Variable Resistor	B1K EVU-E2A	ロータリーボリウム	CONTRAST	02
	LB203090	Phone Jack	HLJ0521 STEREO	ホーンジャック	PHONES	02
	LB301780	Phone Jack	HLJ4306 STEREO	ホーンジャック	OUTPUT1/1+2(R)	03
	LB302010	Phone Jack	HSJ0912 ST-Mini	ホーンジャック	BREATH	02
	VE742000	Phone Jack	HLJ4305 MONO.	ホーンジャック	F.SW,SUS.OUT1(L	02
	VE742200	Phone Jack	HLJ4305 STEREO	ホーンジャック	F.VOLUME,F.CONT	02
*	VI662400	Phone Jack	HLJ4306 STEREO	ホーンジャック	OUTPUT2(L/R)	02
	LB500520	DIN Jack	5P TCS4650	DINジャック	MIDI(IN,OUT,THR	03

* New Parts (新規部品)

ランク：Japan only

Ref. No.	Part No.	Description		部品名	Remarks	ランク
☆	VH812200	Angle Bracket-H,Jack		ＪＫアングル(Ｈ)	JK1-10(OUT-BRE	03
☆	VH812300	Angle Bracket-H,Jack		ＪＫアングル(Ｍ)	JK12-14(M1D1)	02
☆	NX808430	Circuit Board	CARD	ＣＡＲＤシート		
	VC694800	Semiconductive Cera. Cap.	0.1μ 25V Z	半導体セラコン		01
	VF821100	Connector,IC Card	38P	ＩＣカード用コネクタ	DATA	06
☆	VH985300	Connector,IC Card	50P	ＩＣカード用コネクタ	WAVEFORM	
	NA115670	Circuit Board	MK	ＭＫシート		09
	1F003450	Diode	1SS133	ダイオード		01
	NA109720	Circuit Board	PC	ＰＣシート		07
	1G001390	IC	RC4558D-Y	ＩＣ	OP AMP	03
	IC232040	Transistor	2SC2120 F	トランジスタ		03
	1F000040	Diode	1S1555	ダイオード		01
☆	VI692000	Zener Diode	05A25.1Y 5.1V	ツェナーダイオード		01
	HT370250	Trimmer Potentiometer	B50K 3P	半固定抵抗	Offset adjust	02
	HT370260	Trimmer Potentiometer	B100K 3P	半固定抵抗	Gain adjust	02
☆	VH709600	Circuit Board	PS	ＰＳシート	J	
☆☆	VH709700	Circuit Board	PS	ＰＳシート	U,C	
	VH709800	Circuit Board	PS	ＰＳシート	H,D,A,B	
	IG136200	IC	SC-3052V	ＩＣ	+5V 2A	06
	XD340001	IC	AN78M12F	ＩＣ	REGULATOR +12V	03
	XD342001	IC	AN79M12F	ＩＣ	REGULATOR -12V	03
	1F990300	Diode Stack	S5VB20 3.5A200V	ダイオードスタック		08
	VD488400	Diode Stack	RDF04M 1A 400V	ダイオードスタック		02
	1F008900	Zener Diode	MTZ13C 13V	ツェナーダイオード		01
☆	U1D49100	Electrolytic Cap.	1000μ 25V	ケミコン		02
	U1J49220	Electrolytic Cap.	2200μ 25V	ケミコン		03
☆	UJ63A100	Electrolytic Cap.	10000μ 16V	ケミコン		04
	F1383220	Ceramic Cap.	2200P 400V	規格認定コン		01
	F1383470	Ceramic Cap.	4700P 400V	規格認定コン	H,D,A,B	01
	F1494100	Ceramic Cap.	0.01μ 400V	規格認定コン		01
	VC694800	Semiconductive Cera. Cap.	0.1μ 25V Z	半導体セラコン		01
	GD900760	Coil	3mH PLA302IA	コイル		06
	VF578000	Push Switch	ESB-8236V JUCS	プッシュスイッチ	POWER	03
	KB000310	Fuse	T 500mA 250V	ヒューズ	J	01
	KB000330	Fuse	T 1A 250V	ヒューズ	J	01
	KB000360	Fuse	T 3A 250V	ヒューズ	J	01
	KB001150	Fuse	T 500mA 250V	ヒューズ	U,C	02
	KB001060	Fuse	T 1A 250V	ヒューズ	U,C	02
	KB002650	Fuse	T 3A 250V	ヒューズ	U,C	03
	KB000710	Fuse	T 500mA 250V	ヒューズ	H,D,A,B	02
	KB000760	Fuse	T 3.15A 250V	ヒューズ	H,D,A,B	02
	KB001770	Fuse	T 1A 250V	ヒューズ	H,D,A,B	02
	LB201530	Fuse Holder	PC-FH1	ヒューズホルダー		01
	1L000680	Insulation Sheet	BFG-20	放熱シート		01
	B1030106	Bind Head Tapping Screw	3.0×10 ZNC2Y	ﾊﾞｲﾝﾄﾞﾀｯﾋﾟﾝｸﾞﾈｼﾞ	(5pcs)	01
	VG782900	Floppy Disk Drive Unit	D357B 3.5inch	ＦＤドライブユニット		26
	VE460300	Variable Resistor	10K RK1241110	ロータリーボリウム	PITCH BEND	03
	HS412160	Variable Resistor	10K K161100S	ロータリーボリウム	MODULATION 1	03
☆	V1666700	Variable Resistor	10K RK1631110	ロータリーボリウム	MODULATION 2	03
	VF931200	LCD	DMF-5005N	液晶ディスプレイ		28
	VD279200	AC Cord	7A 2.5m	電源コード	J	04
	VD279400	AC Cord	10A 2.5m	電源コード	U	06
	VD279500	AC Cord	10A 2.5m	電源コード	C	07
	VD280400	AC Cord	2.5A 2.5m	電源コード	H,D	06
	VD279700	AC Cord	7.5A 2.5m	電源コード	A	06
	VH890400	AC Cord	6A 2.5m	電源コード	B	08
☆	XG620A00	Power Transformer		電源トランス	J	
☆☆	XG621A00	Power Transformer		電源トランス	U,C	
	XG822A00	Power Transformer		電源トランス	H,D,A,B	10

☆ New Parts (新規部品)

ランク : Japan only

■ OVERALL ASSEMBLY (総組立)



Ref. No.	Part No.	Description		部品名	Remarks	ランク
* 1	VH809100	Control Panel		コントロールパネル		25
2	VD774000	Knob		ツマミ	VOLUME, D.ENTRY	01
* 3	VH810000	Escutcheon, Slide Volume		ｽﾗｲﾄﾞﾎﾞﾘｭｰﾑｴｽｶｯｼｮﾝ		02
* 4	VH810200	Dust Proof Cloth-2		防塵クロス(2)		01
* 5	VH812800	Card Guide		カードガイド		06
* 6	NX808430	Circuit Board	CARD	CARDシート		
* 7	VH811500	Function Keys	SHIFT,F1-8,EXIT	ファンクションキー		03
* 8	V1250800	Rotary Knob		ロータリーツマミ	Data entry Dial	01
* 9	VH810400	Knob-A	(×8)	ノブA(8連)	(4pcs)	02
* 10	V1524400	Knob-B	(×3) 7,8,9	ノブB(3連)	VWX,YZ',.&-	02
* 11	V1524500	Knob-C	(×3) 4,5,6	ノブC(3連)	MNO,PQR,STU	02
* 12	V1524600	Knob-D	(×3) 1,2,3	ノブD(3連)	DEF,GHI,JKL	02
* 13	V1524700	Knob-E	(×3) 0,-,ENTER	ノブE(3連)	ABC,/:,SPACE	02
* 14	V1524300	Knob-G	(×3)	ノブG(3連)	' ,JUMP/MARK	01
* 15	V1534600	Knob-H	(×3) ↑(center	ノブH(3連)	-1/NO, +1/YES	03
* 16	V1537200	Knob-I	(×3) ←,↓,→	ノブI(3連)		03
* 17	VH810500	Knob-J	(×4)	ノブJ(4連)	' ,LOCATE,	01
* 18	VH810600	Knob-K	(×3)	ノブK(3連)	RECORD,STOP,RUN	01
* 19	VH811800	LCD Filter		保護板		06
* 20	VH811400	Escutcheon, LCD		LCDエスカッション		05
21	VF931200	LCD	DMF-5005N	液晶ディスプレイ		28
* 22	VH799200	Circuit Board	PNAB	PNABシート		
* 23	VH810100	Dust Proof Cloth-1		防塵クロス(1)		01
* 24	VH799400	Circuit Board	PNC	PNCシート		
* 25	V1742200	Sheild Sheet		シールドシート		03
* 26	NX808420	Circuit Board	JKAN	JKANシート		
* 27	VH810700	Angle Bracket	Center	センターアングル		08
* 28	VH809500	End Block	Left	拍子木(左)		09
* 29	VH809900	Side Board	Left	側板(左)		04
* 30	VH809700	Shield Plate	Left	シールド板(左)		07
* 31	V1625800	Wheel Assembly		ホイールAss'y		
32	VG782900	Floppy Disk Drive Unit	D357B 3.5inch	FDDドライブユニット		26
* 33	VH813000	Angle Bracket, FDD		FDD金具		04
* 34	V1572100	Keyboard Assembly	FS C61	鍵盤Ass'y		36
* 35	VH809200	End Block	Right	拍子木(右)		07
* 36	VH809600	Shield Cover	Right	シールド板(右)		05
37	VH809800	Side Board	Right	側板(右)		04
* 38	VH810900	Angle Bracket-L, Earth		アースアングル(L)		05
* 39	V1474000	Angle Bracket-S, Earth		アースアングル(S)		01
* 40	XG620A00	Power Transformer		電源トランス	J	
40	XG621A00	Power Transformer		電源トランス	U,C	
* 40	XG622A00	Power Transformer		電源トランス	U,D,A,B	10
41	VD279200	AC Cord	7A 2.5m	電源コード	J	04
41	VD279400	AC Cord	10A 2.5m	電源コード	U	06
41	VD279500	AC Cord	10A 2.5m	電源コード	C	07
41	VD280400	AC Cord	2.5A 2.5m	電源コード	U,D	08
41	VD279700	AC Cord	7.5A 2.5m	電源コード	A	06
41	VH800400	AC Cord	6A 2.5m	電源コード	B	08
42	CB811230	Cord Strain Relief	SR-6N-4	コードストッパー	U	02
42	CB806850	Cord Strain Relief	SR-6N3-4	コードストッパー	C	02
42	CB072750	Cord Strain Relief	SR-4N-4	コードストッパー	U,D,B	01
42	CB032840	Cord Strain Relief	SR-5N-4	コードストッパー	A	01
* 43	VH812600	AC Panel		ACパネル	J	02
* 43	V1319500	AC Panel		ACパネル	U	02
* 43	V1319600	AC Panel		ACパネル	C	02
* 43	V1319700	AC Panel		ACパネル	U,D,A,B	02
44	CB825380	Push Button		プッシュボタン	POWER	01
* 45	VH799600	Circuit Board	PS	PSシート	J	
* 45	VH799700	Circuit Board	PS	PSシート	U,C	
* 45	VH799800	Circuit Board	PS	PSシート	U,D,A,B	
* 46	V1580000	Insulation Sheet, AD		AD絶縁シート	C	02
* 47	VH799100	Circuit Board	DN2	DM2シート		
* 48	VH799000	Circuit Board	DN1	DM1シート		
* 49	V1648000	Bottom Cover Assembly		底板Ass'y		15
49-1	VC999400	Foot	205Y4179	ゴム足		01
50	EB330066	Bind Head Screw	3.0×6 FCM3BL	バインドネジ		01
51	E1330086	Bind Head Tapping Screw	3.0×8 FCM3BL	ﾊﾞｲﾝﾄﾞﾀｯﾋﾟﾝｸﾞﾈｼﾞ		01
52	E1340106	Bind Head Tapping Screw	4.0×10 FCM3BL	ﾊﾞｲﾝﾄﾞﾀｯﾋﾟﾝｸﾞﾈｼﾞ		01
53	E1340166	Bind Head Tapping Screw	4.0×16 FCM3BL	ﾊﾞｲﾝﾄﾞﾀｯﾋﾟﾝｸﾞﾈｼﾞ		01
54	EZ000460	Bonding Tapping Screw	3.0×8 FCM3BL	ﾎﾞﾝﾃﾞｨﾝｸﾞﾀｯﾋﾟﾝｸﾞﾈｼﾞ		01
* 55	V1491300	Bonding Tapping Screw	4.0×10 FCM3BL	ﾎﾞﾝﾃﾞｨﾝｸﾞﾀｯﾋﾟﾝｸﾞﾈｼﾞ		
56	EV413038	Toothed Lock Washer	A φ3.0 FCH3BL	歯付座金内歯形		01
		* ACCESSORIES		* 付属品		
*	XH002A00	Floppy Disk	Demo, disk-B	書込済みFD(B)	J	06
		Floppy Disk	3.5inch 1M	フロッピーディスク	U,C,U,D,A,B	
		Plug Cover	200X300	プラグカバー		

* New Parts (新規部品)

ランク : Japan only

■ KEYBOARD ASSEMBLY (鍵盤Ass'y)



Ref. No.	Part No.	Description		部品名	Remarks	ランク
*	V1572100	Keyboard Assembly	FS C61	鍵盤Ass'y		36
1	NB107600	Black Key Assembly		黒鍵Ass'y		03
2	NB107540	White Key Assembly	C,F	白鍵Ass'y		03
2	NB107550	White Key Assembly	D	白鍵Ass'y		03
2	NB107560	White Key Assembly	B,E	白鍵Ass'y		03
2	NB107570	White Key Assembly	G	白鍵Ass'y		03
2	NB107580	White Key Assembly	A	白鍵Ass'y		03
2	NB107590	White Key Assembly	C'	白鍵Ass'y		03
3	AA055430	Key Spring		鍵バネ		02
4	CB045760	Stopper		ストッパー		02
5	EZ000400	Spacer	W00374 4.0×5	スペーサー		01
6	NA109720	Circuit Board	PC	PCシート		07
7	PB000470	PC Sensor	(L)	PCセンサー		16
8	NB116200	Key Switch Unit	FS	MKスイッチユニット		19
8-1	NA115670	Circuit Board	MK	MKシート		09
8-2	NB107120	Key Switch Assembly	12Q FS	スイッチAss'y		08
8-3	NB107410	Key Switch Assembly	13K FS	スイッチAss'y		08
9	CC030570	Felt	821×6×3 VH	フェルト(白)		03
10	ED330106	Bind Head Screw	3.0×10 PCH3BL	バインド小ネジ		01
11	ED330166	Bind Head Screw	3.0×16 PCH3BL	バインド小ネジ		01

*New Parts (新規部品)

ランク: Japan only

■WHEEL ASSEMBLY（ホイールAss'y）



Ref. No.	Part No.	Description		部品名	Remarks	ランク
	VI625800	Wheel Assembly		ホイールAss'y		
1	VE469300	Variable Resistor	10K RK1241110	ロータリーボリウム	PITCH BEND	03
2	US412160	Variable Resistor	10K K1811005	ロータリーボリウム	MODULATION 1	03
※3	VI666700	Variable Resistor	10K RK1631110	ロータリーボリウム	MODULATION 2	03
4	VF536800	Frame		フレーム		01
5	EW600110	Wheel Ring	φ12.0	CS形止め輪	PITCH BEND	01
6	VC792800	Spring		リターンスプリング	PITCH BEND	01
7	VF537400	Wheel		ホイール		02
8	C8810020	Wheel Tube		ホイールチューブ		02

※New Parts（新規部品）

ランク：Japan only